

# Technics

Turntable System

## SL-1200MK2

### Operating instructions



**“Warning”:**

**To reduce the risk of fire or electric shock, do not expose this appliance to rain or moisture.”**

Before operating this set, please read these instructions completely.

The model number of this product may be found on the back of the unit, and the serial number on the bottom of the unit. Please note the model and serial numbers of this unit in the space provided and retain this booklet as a permanent record of your purchase to aid identification in the event of theft.

MODEL NUMBER SL-1200MK2

SERIAL NUMBER \_\_\_\_\_


Thank you for purchasing the SL-1200MK2.  
 For optimum performance and safety, please read these instructions carefully.


*Dear Stereo Fan*

**Technics.** The science of sound. Our name represents over 100 high quality audio products, in every price range. From our revolutionary direct drive turntables to our highly acclaimed linear phase speakers, Technics quality and value have become almost legendary among audio enthusiasts. Our truly complete selection of turntable (including belt-drive and quartz-locked, direct-drive models with varying degrees of automation) now includes an exciting line of linear tracking turntables with zero tracking error. Another innovation, direct drive cassette decks, is available in both slim and micro formats. In fact, with the Technics micro series, you can assemble an entire system of the highest quality with truly compact dimensions.


Features like our new computer-drive new class-A amplification and quartz-synthesizer tuning have created tremendous excitement among reviewers and customers alike. Amplifiers, tuners, headphones, microphones, cartridges, open-reel decks, sound processors—we are proud of all our high quality equipment and we are constantly seeking to improve our products, in terms of performance and handling ease. In addition, our confidence in the reliability of our merchandise (demonstrated by our warranties) and the reasons for our enormous and rapid growth become obvious.

**Parts identification**







**CAUTION**  
 RISK OF ELECTRIC SHOCK  
 DO NOT OPEN
























CAUTION: TO REDUCE THE RISK OF ELECTRIC SHOCK, DO NOT REMOVE SCREWS. NO USER-SERVICEABLE PARTS INSIDE. REFER SERVICING TO QUALIFIED SERVICE PERSONNEL.



The lightning flash with arrowhead symbol, within an equilateral triangle, is intended to alert the user to the presence of uninsulated "dangerous voltage" within the product's enclosure that may be of sufficient magnitude to constitute a risk of electric shock to persons.



The exclamation point within an equilateral triangle is intended to alert the user to the presence of important operating and maintenance (servicing) instructions in the literature accompanying the appliance.



## Before use

### Caution:

Never connect the AC power plug before assembly has been completed.

Attach the dust cover last, so that assembly and adjustments can be made most conveniently.

### ■ Checklist of parts

Turntable unit .....	1
Turntable platter .....	1
Turntable mat .....	1
Dust cover .....	1
45-rpm adaptor .....	1
Balance weight .....	1
Auxiliary weight .....	1
Headshell .....	1
Overhang gauge .....	1
Shell weight .....	1

## Assembly and set-up

### ■ Installation of turntable platter

1. Place the turntable platter on the center spindle.

#### Note:

The rotor is connected to the underside of the turntable platter. (The magnet of the motor is attached to the turntable platter.) To maintain optimum performance, extra care should be taken to prevent adhesion of dust or iron filings to the magnet and not to damage the magnet by dropping it.

Do not remove or loosen the screws. Should the position of the fixed magnet be altered by loosening the securing screws, the rated performance of the unit cannot be guaranteed. (See Fig. 2.)

2. Place the turntable mat on the platter.

### ■ Installation of cartridge (See Fig. 3.)

When you install a cartridge, refer to the operation instructions of that cartridge.

During installation, attach the stylus protector to guard the stylus tip from damage.

1. Connect the lead wires to the cartridge terminals.  
The terminals of most cartridges are color coded. Connect each lead wire to the terminal of the same color.  
**White (L+)** ..... **Left channel+**  
**Blue (L-)** ..... **Left channel-**  
**Red (R+)** ..... **Right channel+**  
**Green (R-)** ..... **Right channel-**
2. Install a cartridge to the headshell, and tighten it with screws provided with the cartridge.

#### Note:

Use the shell weight only for a lightweight cartridge (less than 6 g). (See Fig. 4.)

### ■ Adjustment of overhang (See Fig. 5.)

1. Insert the headshell into the gauge.
2. Loosen the mounting screws and move the cartridge forward or backward until the stylus tip lines up with the edge of the gauge.

3. Tighten the mounting screws without moving the cartridge.

#### Note:

Your cartridge is now adjusted for lowest tracking error and minimum distortion.

This gauge is exclusively designed for this tonearm.

### ■ Installation of headshell (See Fig. 6.)

Insert the headshell into the front end of the tubular arm, and turn the locking nut clockwise (in the direction shown by the arrow "A"), with the headshell firmly held horizontally.

### ■ Installation of balance weight (See Fig. 7.)

Place the balance weight on the rear shaft of the tonearm.

#### Note:

In case the cartridge weight exceeds 10 g, it is necessary to fix the attached auxiliary weight over the rear shaft of the arm.

With this auxiliary weight in use, it is possible to use any cartridge whose weight is in the range of 9.5–13 g. (See Fig. 8.)

### ■ Adjustments of horizontal zero (0) balance and stylus pressure

1. Remove the stylus protector, if your cartridge has a detachable one. Be careful not to touch your fingers to the stylus tip.
2. Release the arm clamp and lift the tonearm from the arm rest to free it.
3. Turn the entire balance weight clockwise (indicated by the arrow "A") or counterclockwise (indicated by the arrow "B") until the tonearm is approximately balanced horizontally (floats freely). (See Figs. 9 and 10.)

#### Note:

##### (A)

Excessive forward advancement of the balance weight causes the cartridge side to be lowered.

##### (B)

Excessive backward retreatment of the balance weight causes the cartridge side to be raised.

##### (C)

Upon balancing between the balance weight and cartridge, the tonearm is held horizontal.

During the adjustment of the horizontal zero (0) balance, be careful that the stylus tip of the cartridge does not contact the turntable mat or turntable base.

4. After the tonearm is horizontally zero (0) balanced, temporarily refasten the tonearm with the arm clamp.
5. Hold the balance weight stationary with one hand as shown in the picture, and rotate only the stylus-pressure ring to bring the numeral "0" of the ring into alignment with the center line on the tonearm rear shaft. (See Fig. 11.)  
The adjustment of the horizontal zero (0) balance is now completed.
6. After adjusting the horizontal zero (0) balance, turn the balance weight in the direction of the arrow and align to the correct stylus pressure. (See Fig. 12.)  
(Follow the cartridge manufacturer's recommendation.)

## Placement

As the stylus-pressure ring moves in step with the balance weight, proper stylus pressure can be selected by directly reading the graduated ring.

### ■ Adjustment of anti-skating control

Set the anti-skating control knob to the same value as the stylus pressure. (See Fig. 13.)

### ■ Adjustment of tonearm height (See Fig. 14.)

The height of the tonearm can be adjusted up to 6 mm and a scale is provided on the adjust ring in 0.5 mm increments. Be sure to set the proper arm height using the adjust scale and referring to the table below.

Before adjusting the tonearm height, unlock the tonearm lock by turning the arm lock knob.

Height of cartridge (mm) (H)	Scale reading on the arm-height adjust ring
15	0
16	1
17	2
18	3
19	4
20	5
21	6

For example, if the cartridge height is 17.5 mm, the arm-height adjust ring should be positioned at the intermediate location between 2 and 3 on the scale. (See Fig. 14.)

#### Caution:

Be sure to lock the tonearm by turning the arm lock knob in the direction indicated by the arrow after finishing the height adjustment for the tonearm.

### ■ Installation of dust cover (See Fig. 15.)

Place the dust cover in position from directly above, holding it at both sides. For detaching the dust cover, be certain first to raise it as illustrated before removal.

#### Note:

Opening or closing of the dust cover during play should be avoided. This may not only cause undesired vibrations, but also result in skipping of the stylus.

If you must open the dust cover during play, do so as gently as possible.

■ Place the unit in a stable and horizontal position, where there is little or no vibration.

■ Locate the unit as far away from the speakers as possible and isolate the unit from sound radiation from them.


■ Do not place the unit where it is exposed to direct sun, dust, moisture or heat.

■ Keep it in a well ventilated place.

■ When a radio is placed too close to the turntable and is played while the turntable is in operation, interference to AM/FM reception may result.


### ■ Adjustment of turntable height

The legs/insulators also have functions for adjusting the height of the turntable unit itself. After installing the unit in the place for use, adjust the legs to stabilize the main body horizontally.



## Connections

### ■ Connect the output terminals (See Fig. 16.)



#### Note:

Be sure to connect the ground terminal firmly to the amplifier or receiver. If this connection is not made or is loose, a power source "HUM" will result.

### ■ Connect the AC power plug

Connect the AC power plug to an AC wall socket.

## How to operate

1. Place a record on the turntable mat.
2. Turn the power switch to the "on" position. (See Fig. 17.)  
The speed indicator for 33-1/3 rpm and the strobe-illuminator will all light up.  
**Note:**  
Since the unit has been designed to select 33-1/3 rpm automatically each time you push the power switch to "on", push the 45 rpm speed select button if you play a 45 rpm record (See Fig. 18.)
3. Remove the stylus protector, if your cartridge has a detachable one.
4. Release the arm clamp.
5. Push the start/stop button. (See Fig. 19.)  
The turntable platter will start to rotate.
6. Set the cueing lever to the up position. (See Fig. 20.)
7. Move the tonearm over the desired groove.
8. Set the cueing lever to the down position. (See Fig. 21.)  
The tonearm will descend slowly onto the record and play will begin.
9. When play is finished, move the tonearm to the arm rest; secure the tonearm with the arm clamp.
10. Push the start/stop button.  
After the turntable is brought to a stop by means of the electronic brake, turn off the power.  
**Note:**  
The electronic brake does not function if the power switch is turned off before the start/stop button is pushed.

### ■ How to suspend play

Set the cueing lever to the "up" position.  
The stylus tip of the cartridge will be lifted from the record.

### ■ When you play a 45-rpm record with a large center hole

Place the 45-rpm adaptor on the center spindle. Push the 45 speed select button.

#### **Note:**

Keep the adaptor stored on the adaptor hole when not playing a 45-rpm record (donut type).  
Take the adaptor out in the manner shown in Fig. 22 when using the adaptor.

### ■ Stylus illuminator (See Fig. 23.)

This unit is provided with a stylus illuminator for illuminating the stylus tip during play.

By pressing the stylus illuminator switch, the stylus illuminator is raised into position for illuminating the stylus tip. When not in use, keep the stylus illuminator lowered through depression.

#### **Note:**

The switch must be firmly engaged.

Incomplete depression of the switch will not raise the illuminator even though the lamp is lit.

## Adjustments

### ■ Pitch control (fine adjustment of speed) (See Figs. 24 and 25.)

When the pitch control knob is located at the center of the position after turning on the power, the green LED indicator is lit showing the operating condition for the predetermined speed (either 33-1/3 or 45 rpm).

Figures on the indicator show approximate percentages for variable pitch control.

When the strobe dots in 4 stages marked at the peripheral edge of the turntable appear to be stationary, variation of individual pitches is shown. (See Fig. 25.)

When (1) appears stationary, it shows a +6% pitch variation.

When (2) appears stationary, it shows a +3.3% pitch variation.

When (3) appears stationary, it shows normal turntable speed, 33-1/3 or 45 rpm.

When (4) appears stationary, it shows a -3.3% pitch variation.

#### **Note:**

The strobe-illumination of this unit employs a strobe-illuminator LED synchronized with the precise quartz frequency.

For fine adjustment of the turntable speed, be sure to effect the adjustment according to the LED illumination.

The LED illumination is not synchronized using fluorescent lamps.

### ■ Adjustment of arm-lift height

(See Figs. 26 and 27.)

The arm-lift height (distance between the stylus tip and record surface when the cueing lever is raised) has been adjusted at the factory before shipping to approximately 8~13 mm.

If the clearance becomes too narrow or too wide, turn the adjustment screw clockwise or counterclockwise while pushing the arm lift down.

#### **Clockwise rotation**

—distance between the record and stylus tip is decreased.

#### **Counterclockwise rotation**

—distance between the record and stylus tip is increased.

#### **Note:**

As the adjusting screw has a hexagonal head, be sure to make the adjustment while depressing the arm lift, or the screw will not move freely.

Also be sure that the hexagonal head retracts correctly into the arm lift when the latter is released.

## Notes and maintenance

- **Use utmost care when handling the platter and when placing it on the motor shaft to prevent possible damage to the magnet.**
- **Do not turn "on" the power supply, with the turntable platter detached.**
- **Before detaching or attaching the headshell, be sure to turn the power of the amplifier or receiver off.**  
Detaching or attaching of the headshell with the volume control turned up may cause damage to the speakers.
- **When play is finished, be sure to secure the tonearm with the arm clamp.**  
After play is finished, if the unit is not to be used for some time, care should be taken to secure the tonearm to protect the stylus tip.  
For the same reason, the stylus protector should also be attached.
- **Dust and dirt should be carefully removed from stylus tip or records.**  
Dust and dirt on the stylus tip or record may not only result in deterioration of tone quality, but also cause undue wear of the record and the stylus tip itself.  
Special stylus tip brushes and record cleaners can be purchased in most electronic supply houses.
- **Wipe the headshell terminals from time to time.**  
Dust and dirt at the headshell terminals may result in increased "HUM" noise or intermittent sound. Use a soft dry cloth to clean the headshell terminals.
- **Wipe the dust cover and turntable base with a soft, dry cloth.**  
Never use any cleaners containing alcohol, benzine or thinner.  
Use of a chemical dust cloth should also be avoided. Be sure that the dust cover is not exposed to insecticide spray.  
To remove stubborn fingerprints or grease spots, detach the dust cover and disconnect the AC power plug.  
Use a soft cloth slightly moistened with a mild soap and water solution.  
Do not wipe the dust cover during play, or the tonearm may be attracted toward the dust cover due to the generation of static electricity.
- **Lubrication (See Fig. 28.)**  
Apply 2 or 3 drops of oil once after every 2000 hours of operation.  
The time interval is much longer than that for conventional type motors (200–500 hours).  
Please purchase original oil. (Part number is SFWO 010.)
- **Transportation of the unit to distant places for removal and the like.**  
Pack up the unit in the reverse order to that for unpacking, using the packing materials furnished when the unit was purchased. Should there be no such packing materials, be sure to take the following steps.
  - Remove the turntable platter together with the turntable mat, and wrap it up to prevent any damage to them.
  - Return the tonearm to the arm rest, and affix it with tape or the like.
  - Remove the balance weight and the headshell/cartridge from the tonearm and then wrap them up to avoid any damage to them.
  - Wrap up the turntable base with a blanket or soft paper also to prevent any possible damage to it.

## Suggestions for safety

Before using this unit, be sure to read applicable items of the operating instructions and these safety suggestions carefully; and afterwards keep them handy for future reference. Take special care to follow the warnings indicated on the unit itself as well as in the operating instructions.

1. **Avoid places where there is water or humidity.**  
Do not use this unit near a bathtub, washbasin, swimming pool, or the like. Damp basements should also be avoided.
2. **Don't allow water or any foreign object to get inside this unit.**  
Don't place small metal objects or anything containing liquid on or near the unit.
3. **Avoid placement of the unit where it will be exposed to the direct rays of the sun, or where ventilation is inadequate.**  
Don't place this unit in a bookcase or between cabinets, unless proper ventilation is provided, or where curtains or furniture may obstruct the ventilation holes.
4. **Place this unit away from heat-emitting appliances.**  
Never place this unit on or near a radiator, heat register, stove, or any other heat-emitting equipment. (Including Amplifiers).
5. **Placement**  
Place the unit on a stable, vibration-free, level shelf or stand.
6. **Use of a cart or stand.**  
When deciding on a cart or stand, be sure to use only with the cart or stand recommended by the manufacturer.
7. **Wall or ceiling installation.**  
If the unit is to be mounted on a wall or ceiling, be sure to do so only as recommended by the manufacturer.
8. **Check the voltage rating of this unit before connecting the unit to a power supply.**  
Be sure to connect the unit only to the type of power supply indicated in the operating instructions, or as indicated on the unit itself.
9. **Care of the power cord and plug.**  
Take care that the cord is not bent sharply (especially near its connection to the unit or near the plug), that nothing is placed on it, and that it is not pinched, or crushed. Never take hold of the plug or cord if your hand is wet, and always be sure to grasp the plug body when connecting or disconnecting it.
10. **If the unit will not be used for a long period of time:**  
Be sure to disconnect the power cord.
11. **Maintenance**  
Refer to the operating instructions for details.
12. **Never attempt repairs yourself:**
  - (a) If the power cord or plug is damaged.
  - (b) If a foreign object or liquid falls into the unit.
  - (c) If the unit is exposed to rain.
  - (d) If the unit does not function normally, or if operation shows an unusual change.
  - (e) If the unit has been dropped and the cabinet or chassis is damaged... etc.Unplug the power cord and consult with a qualified technician (or the dealer from whom the unit was purchased or the nearest servicenter).
13. **Repairs**  
Except for adjustments explained in the operating instructions, do not attempt any repairs yourself. Be sure to request service from a qualified technician (or your dealer or nearest service center).

## Specifications

### ■ General

<b>Power supply:</b>	120 V, AC, 60 Hz
<b>Power consumption:</b>	14 W
<b>Dimensions:</b>	45.3×16.2×36 cm
<b>(W×H×D)</b>	(17-27/32"×6-19/64"×14-11/64")
<b>Weight:</b>	12.5 kg (27.6 lb)

### ■ Turntable section

<b>Type:</b>	Quartz direct drive Manual turntable
<b>Drive method:</b>	Direct drive
<b>Motor:</b>	Brushless DC motor
<b>Turntable platter:</b>	Aluminum diecast Diameter 33.2 cm (13-5/64") Weight 2 kg (4.4 lb.)
<b>Turntable speeds:</b>	33-1/3 rpm and 45 rpm
<b>Starting torque:</b>	1.5 kg·cm (1.3 lb·in)
<b>Build-up characteristics:</b>	0.7 s. from standstill to 33-1/3 rpm
<b>Braking system:</b>	Electronic brake
<b>Wow and flutter:</b>	0.01% WRMS* 0.025% WRMS (JIS C5521) ±0.035% peak (IEC 98A Weighted)

\*This rating refers to turntable assembly alone, excluding effects of record, cartridge or tonearm, but including platter. Measured by obtaining signal from built-in frequency generator of motor assembly.

<b>Rumble:</b>	-56 dB (IEC 98A Unweighted) -78 dB (IEC 98A Weighted)
----------------	--

### ■ Tonearm section

<b>Type:</b>	Universal
<b>Effective length:</b>	230 mm (9-1/16")
<b>Arm height adjustment range:</b>	0-6 mm
<b>Overhang:</b>	15 mm (19/32")
<b>Effective mass:</b>	12 g (without cartridge)
<b>Offset angle:</b>	22°
<b>Friction:</b>	Less than 7 mg (lateral, vertical)
<b>Tracking error angle:</b>	Within 2°32' (at the outer groove of 30 cm (12") record) Within 0°32' (at the inner groove of 30 cm (12") record)
<b>Stylus pressure adjustment range:</b>	0-2.5 g
<b>Applicable cartridge weight range:</b>	6-10 g 13.5-17.5 g (including headshell)
<b>(with auxiliary weight):</b>	9.5-13 g 17-20.5 g (including headshell)
<b>(with shell weight):</b>	3.5-6.5 g 11-14 g (including headshell)
<b>Headshell weight:</b>	7.5 g

Specifications subject to change without notice.  
Weight and dimensions shown are approximate.

## Features

### ■ Total quartz locked continuous pitch adjustment about ±8%

Quartz-phase-locked control means almost perfect accuracy of turntable rotation.

But with most quartz turntables, this accurate control circuit must be cut out when the pitch control is employed.

With the SL-1200MK2, however, pitch is variable continuously (analogically) by up to approximately ±8% under total quartzlocked control. The pitch is controlled with a large sliding lever, located to the right of the turntable platter.

Four lines of platter markings are also provided indicating +6%, +3.3%, 0% (exact rated speed) and -3.3% change from rated speed.

### ■ Aluminum diecast cabinet and special heavy rubber base material provide acoustic isolation

The effects of external vibrations are dramatically reduced in the turntable by this new turntable construction.

The turntable base is precision-made aluminum diecast. And the underside of the main base is made of a heavy rubber material which has excellent vibration resistance and absorbing characteristics. The turntable platter is also vibration-damped with specially fabricated rubber matting in the underside along with the thick turntable sheet (rubber mat). Four large-size insulating feet also help to absorb unwanted vibrations.

These features make the SL-1200MK2 ideal for use with extra-high sound pressure levels.

### ■ High torque for fast starts

The integral rotor/platter motor delivers 1.5 kg·cm (1.3 lb·in) starting torque. This high torque gives very quick starts enabling the platter to reach 33-1/3 rpm within 0.7 s. (a quarter of a turn). This is a big advantage in many professional applications where fast cueing is a necessity.

### ■ High sensitivity, low mass, gimbal suspension tonearm

The highly sensitive tonearm features a genuine gimbal suspension, the rotational center of which is precisely defined at one point. Bearings are finished to a tolerance of ±0.5 microns. This, and the extra-closeness of pivot center to the bearings, result in the minimal friction of 7 mg (0.007 g) for both horizontal and vertical movement. Add to this the low 12-gram effective tonearm mass (including headshell, without cartridge) and you have a tonearm compatible with the wide range of compliances found in today's cartridges. If you choose a popular high compliance MM cartridge, the low range resonance frequency will appear in the correct area to avoid warp frequencies of records, but without entering the low end of the audio spectrum. This tonearm is provided with a computer designed, light-weight, high-rigidity headshell made of single-piece diecast aluminum to resist partial vibration. The universal design allows headshell interchangeability. Contacts are gold-plated.



### ■ Helicoid tonearm height adjustment

Arm height is adjustable within a range of 6 mm to accommodate varying cartridge dimensions. Adjustments are done with a precision-made helicoid.

### ■ Stylus illuminator for low-light conditions

#### ■ Other fine features

- Quick stops are achieved with a fully electronic braking system.
- A strobe illuminator is provided. The stroboscope is controlled by the extremely stable quartz oscillator, rather than potentially unstable AC line frequency.
- Power on/off control built-into strobe illuminator for ease of operation.
- Soft-touch start/stop switch allowing precision control capability without the annoyance of accidental operation.
- Technics integral rotor/platter motor construction with full cycle detection FG.

**Note:**

This equipment generates and uses radio frequency energy and if not installed and used properly, that is, in strict accordance with the manufacturer's instructions, may cause interference to radio or television reception. It has been type tested and found to comply with the limits for a Class B computing device in accordance with the specifications in Subpart J of Part 15 of FCC Rules, which are designed to provide reasonable protection against such interference in a residential installation. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures;

- reorient the receiving antenna
- relocate this equipment with respect to the receiver
- move this equipment away from the receiver
- plug this equipment into a different outlet so that this equipment and receiver are on different branch circuits.

If necessary, the user should consult the dealer or an experienced radio/television technician for additional suggestions.


The user may find the following booklet prepared by the Federal Communications Commission helpful: "How to Identify and Resolve Radio-TV Interference Problems." This booklet is available from the U.S. Government Printing Office Washington, D.C., 20402 Stock No. 004-000-00345-4.

---

**Panasonic Company**  
**Division of Matsushita Electric**  
**Corporation of America**  
One Panasonic Way, Secaucus,  
New Jersey 07094

**Panasonic Hawaii, Inc. ("PHI")**  
91-238 Kauhi St. Ewa Beach P.O. Box 774  
Honolulu, Hawaii 96808-0774

**Panasonic Sales Company,**  
**Division of Matsushita Electric**  
**of Puerto Rico, Inc.**  
Ave. 65 De Infanteria, KM 9.7  
Victoria Industrial Park  
Carolina, Puerto Rico 00630



**Matsushita Electric of Canada Limited,**  
5770 Ambler Drive, Mississauga, Ontario,  
L4W 2T3

©Matsushita Electric  
Industrial Co. Ltd.  
All Rights Reserved.  
Unauthorized  
Copying and Distribution  
is a Violation of Law.