

Panasonic®


Operating Instructions

Expandable Digital Cordless
Answering System

Model No. **KX-TG8231**

with 2 Handsets

Model No. **KX-TG8232**



Model shown is KX-TG8231.

DECT
6.0

This unit is compatible with Caller ID. To use this feature, you must subscribe to the appropriate service offered by your service provider/telephone company.

Charge the handset batteries for 7 hours before initial use.

Please read these Operating Instructions before using the unit and save them for future reference.

For assistance, visit our website:

<http://www.panasonic.com/help> for customers in the U.S.A. or Puerto Rico.


Table of Contents

Introduction		Multi-unit Operation	
Product information	3	Operating additional handsets	37
Accessory information	3	Intercom	37
Important safety instructions	5	Transferring calls between handsets, conference calls	37
For best performance	7	Registering a handset to a base unit	38
Preparation		Useful Information	
Controls	9	Belt clip	40
Displays	10	Headset (optional)	40
Connections	11	Error messages	41
Battery installation and replacement	12	Troubleshooting	42
Battery charge	13	FCC and other information	48
Screen saver mode	14	Specifications	51
Symbols used in these operating instructions	14	Customer services	52
Setting up the unit before use	14	Warranty	53
Making/Answering Calls		Index	
Making calls	16	Index	55
Answering calls	16		
Useful features during a call	17		
Phonebook			
Handset phonebook	19		
Copying handset phonebook entries	22		
Caller ID Service			
Using Caller ID service	23		
Caller list	24		
Programming			
Programmable settings	26		
Answering System			
Answering system	30		
Turning the answering system on/off	30		
Greeting message	30		
Listening to messages using the base unit	31		
Listening to messages using the handset	32		
Remote operation	33		
Answering system settings	34		
Voice Mail Service			
Using Voice Mail service	36		

Introduction

Product information

Thank you for purchasing a Panasonic cordless telephone.
 These operating instructions can be used for the following models:




Accessory information

Supplied accessories

No.	Accessory item	Order number	Quantity	
			KX-TG 8231B	KX-TG 8232B
①	AC adaptor for base unit	PQLV207V	1	1
②	Telephone line cord	PQJA10075Z	1	1
③	Rechargeable batteries AAA (R03) size	HHR-4DPA (Part No. HHR-55AAABU)	2	4
④	Handset cover ^{*1}	PQYNTG8200ER	1	2
⑤	Belt clip	PQKE10481Z1	1	2
⑥	Charger	PQLV30056Y	–	1
⑦	AC adaptor for charger	PQLV209V	–	1

*1 The handset cover comes attached to the handset.



Introduction

Additional/replacement accessories


Accessory item	Order number
2 rechargeable nickel metal hydride (Ni-MH) batteries, AAA (R03) size	HHR-4DPA
Headset	KX-TCA60, KX-TCA86, KX-TCA88HA, KX-TCA92, KX-TCA93, KX-TCA94, or KX-TCA95
T-adaptor	KX-J66

Expanding your phone system

You can expand the phone system by registering optional handsets to a single base unit.

- A maximum of 6 total handsets (supplied and optional) can be registered to a single base unit.

Handset (optional): KX-TGA820



Sales and support information

- To order additional/replacement accessories, call 1-800-332-5368.
- TTY users (hearing or speech impaired users) can call 1-866-605-1277.

Introduction

Important safety instructions

When using the product, basic safety precautions should always be followed to reduce the risk of fire, electric shock, or personal injury.

1. Read all instructions carefully.
2. Follow all warnings and instructions marked on the product.
3. Unplug the product from power outlets before cleaning. Do not use liquid or aerosol cleaners. Use a dry soft cloth for cleaning.
4. Do not use the product near water, for example near a bathtub, wash bowl, kitchen sink, etc.
5. Place the product securely on a stable surface. Serious damage and/or injury may result if the product falls.
6. Do not cover slots and openings on the product. They are provided for ventilation and protection against overheating. Never place the product near radiators, or in a place where proper ventilation is not provided.
7. Use only the power source marked on the product. If you are not sure of the type of power supplied to your home, consult your dealer or local power company.
8. Do not place objects on the power cord. Install the product where no one can step or trip on the cord.
9. Do not overload power outlets and extension cords. This can result in the risk of fire or electric shock.
10. Never push any objects through slots in the product. This may result in the risk of fire or electric shock. Never spill any liquid on the product.
11. To reduce the risk of electric shock, do not disassemble the product. Take the product to an authorized service center when service is required. Opening or removing covers may expose you to dangerous voltages or other risks. Incorrect reassembly can cause electric shock when the product is subsequently used.
12. Unplug the product from power outlets and take to an authorized service center when the following conditions occur:
 - A. When the power cord is damaged or frayed.
 - B. If liquid has been spilled into the product.
 - C. If the product has been exposed to rain or water.
 - D. If the product does not work normally by following the operating instructions. Adjust only controls covered by the operating instructions. Improper adjustment may require extensive work by an authorized service center.
 - E. If the product has been dropped or physically damaged.
 - F. If the product exhibits a distinct change in performance.
13. During thunderstorms, avoid using telephones except cordless types. There may be a remote risk of an electric shock from lightning.
14. Do not use the product to report a gas leak, when in the vicinity of the leak.

SAVE THESE INSTRUCTIONS

WARNING

- To prevent the risk of fire or electrical shock, do not expose the product to rain or any type of moisture.

Introduction

- Unplug the product from power outlets if it emits smoke, an abnormal smell, or makes an unusual noise. These conditions can cause fire or electric shock. Confirm that smoke has stopped emitting and contact the Panasonic Call Center at 1-800-211-PANA (1-800-211-7262).
- Do not spill liquids (detergents, cleansers, etc.) onto the telephone line cord plug, or allow it to become wet at all. This may cause a fire. If the telephone line cord plug becomes wet, immediately pull it from the telephone wall jack, and do not use.
- Do not place or use this product near automatically controlled devices such as automatic doors and fire alarms. Radio waves emitted from this product may cause such devices to malfunction resulting in an accident.
- Completely insert the AC adaptor/power plug into the power outlet. Failure to do so may cause electric shock and/or excessive heat resulting in a fire.
- Regularly remove any dust, etc. from the AC adaptor/power plug by pulling it from the power outlet, then wiping with a dry cloth. Accumulated dust may cause an insulation defect from moisture, etc. resulting in a fire.

CAUTION

Installation

- Never install telephone wiring during a lightning storm.
- Never install telephone line jacks in wet locations unless the jack is specifically designed for wet locations.
- Never touch uninsulated telephone wires or terminals unless the telephone line has been disconnected at the network interface.

disconnected at the network interface.

- Use caution when installing or modifying telephone lines.
- Do not touch the plug with wet hands.
- The AC adaptor is used as the main disconnect device. Ensure that the AC outlet is installed near the product and is easily accessible.

Battery

To reduce the risk of fire or injury to persons, read and follow these instructions.

- We recommend using the battery(ies) noted on page 4. **Use only rechargeable battery(ies).**
- Do not mix old and new battery(ies).
- Do not dispose of the battery(ies) in a fire, as they may explode. Check with local waste management codes for special disposal instructions.
- Do not open or mutilate the battery(ies). Released electrolyte is corrosive and may cause burns or injury to the eyes or skin. The electrolyte may be toxic if swallowed.
- Exercise care when handling the battery(ies). Do not allow conductive materials such as rings, bracelets or keys to touch the battery(ies), otherwise a short circuit may cause the battery(ies) and/or the conductive material to overheat and cause burns.
- Charge the battery(ies) provided with or identified for use with this product only in accordance with the instructions and limitations specified in this manual.
- Only use a compatible base unit (or charger) to charge the battery(ies). Do not tamper with the base unit (or charger). Failure to follow these instructions may cause the battery(ies) to swell or explode.

Introduction

Medical

- Consult the manufacturer of any personal medical devices, such as pacemakers or hearing aids, to determine if they are adequately shielded from external RF (radio frequency) energy. (The product operates in the frequency range of 1.92 GHz to 1.93 GHz, and the power output is 125 mW (max.)) Do not use the product in health care facilities if any regulations posted in the area instruct you not to do so. Hospitals or health care facilities may be using equipment that could be sensitive to external RF energy.

Notice for product disposal, transfer, or return

- This product can store your private/confidential information. To protect your privacy/confidentiality, we recommend that you erase the information such as phonebook or caller list entries from the memory before you dispose, transfer or return the product.

For best performance

Base unit location/avoiding noise

The base unit and other compatible Panasonic units use radio waves to communicate with each other.

- For maximum coverage and noise-free communications, place your base unit:
 - at a convenient, high, and central location with no obstructions between the handset and base unit in an indoor environment.
 - away from electronic appliances such as TVs, radios, personal

computers, wireless devices or other phones.

- avoid facing radio frequency transmitters, such as external antennas of mobile phone cell stations (avoid putting the base unit on a bay window or near a window).
- Coverage and voice quality depends on the local environmental conditions.
- If the reception for a base unit location is not satisfactory, move the base unit to another location for better reception.

Environment

- Keep the product away from electrical noise generating devices, such as fluorescent lamps and motors.
- The product should be kept free from excessive smoke, dust, high temperature, and vibration.
- The product should not be exposed to direct sunlight.
- Do not place heavy objects on top of the product.
- When you leave the product unused for a long period of time, unplug the product from the power outlet.
- The product should be kept away from heat sources such as heaters, kitchen stoves, etc. It should not be placed in rooms where the temperature is less than 5 °C (41 °F) or greater than 40 °C (104 °F). Damp basements should also be avoided.
- The maximum calling distance may be shortened when the product is used in the following places: Near obstacles such as hills, tunnels, underground, near metal objects such as wire fences, etc.
- Operating the product near electrical appliances may cause interference. Move away from the electrical appliances.

Introduction


Routine care

- **To clean the product, use a dry soft cloth. The outer surface of the product can be scratched by wiping or rubbing with a hard cloth.**
- Do not use benzine, thinner, or any abrasive powder.

Preparation


Controls

Base unit



- 1 Charge contacts
- 2 Speaker
- 3 [X] (ERASE)
- 4 [▲] (VOL.: Volume up)
- 5 [ANSWER ON] (ANSWER ON indicator)
- 6 [◀◀] (Repeat)
- 7 [■] (STOP)
- 8 [▶] (Message)
Message indicator
- 9 [▼] (VOL.: Volume down)
- 10 [📶] (LOCATOR)
- 11 [▶▶] (Skip)

Handset



- 1 Speaker
- 2 Soft keys
- 3 Joystick
- 4 [TALK]
- 5 [SP-PHONE: Speakerphone]
- 6 Headset jack
- 7 Dial keypad
([*]: TONE)
- 8 [FLASH] [CALL WAIT]
- 9 Receiver
- 10 Display
- 11 [OFF]
- 12 [MUTE] [CLEAR]
- 13 [INTERCOM] [TRANSFER]
- 14 Microphone
- 15 Charge contacts

Preparation


Using the joystick

The handset joystick can be used to navigate through menus and to select items shown on the display, by pushing it up [▲], down [▼], left [◀], or right [▶].




Adjusting the receiver or speaker volume

Push the joystick up or down while talking.



Soft keys

The handset features 2 soft keys and a joystick. By pressing a soft key, or by pressing the center of the joystick, you can select the feature shown directly above it on the display.



Displays

Handset display items




Item	Meaning
	Within range of a base unit <ul style="list-style-type: none"> When flashing: Handset is searching for base unit (page 44).
	Alarm is on. (page 28)
	Handset is on an outside call.
	Speaker is on.
	Ringer volume is off. (page 17, 27)
	Call privacy mode is on. (page 17)
	Handset number
	<ul style="list-style-type: none"> Line is being used by another handset for calling, registration, etc. Answering system is being used by another handset or the base unit.
	Battery level

Menu icons

When in standby mode, pressing down on the center of the joystick reveals the handset's main menu. From here you can access various features and settings.

Icon	Feature
	View Caller ID
	Display settings
	Set date & time

Preparation


Icon	Feature
	Answering device
	Initial settings
	Customer support

Connections

Connect the telephone line cord until it clicks into the base unit and telephone line jack (1). Connect the AC adaptor cord (2) by pressing the plug firmly (3).


Base unit

- Use only the supplied Panasonic AC adaptor PQLV207.
- Use only the supplied telephone line cord.



Charger (KX-TG8232)

- Use only the supplied Panasonic AC adaptor PQLV209.



Note:


- The AC adaptor must remain connected at all times. (It is normal for the adaptor to feel warm during use.)
- The AC adaptor should be connected to a vertically oriented or floor-mounted AC outlet. Do not connect the AC adaptor to a ceiling-mounted AC outlet, as the weight of the adaptor may cause it to become disconnected.
- The unit will not work during a power failure. We recommend connecting a corded telephone to the same telephone line or to the same telephone line jack using a Panasonic T-adaptor (page 4).

Preparation

If you subscribe to a DSL service

Please attach a noise filter (contact your DSL provider) to the telephone line between the base unit and the telephone line jack in the event of the following:

- Noise is heard during conversations.
- Caller ID features do not function properly.




Battery installation and replacement


Important:

- Use only the supplied rechargeable batteries noted on page 3, 6.
- USE ONLY rechargeable Ni-MH batteries AAA (R03) size.
- Do NOT use Alkaline/Manganese/Ni-Cd batteries.
- Ensure correct polarities (+, -) when installing the batteries.
- Wipe the battery ends (+, -) with a dry cloth.
- When installing the batteries, avoid touching the battery ends (+, -) or the unit contacts.
- When replacing batteries, we recommend using the Panasonic rechargeable batteries noted on page 4, 6.

- 1 Press the notch on the handset cover firmly, and slide it in the direction of the arrow.




- 2 Insert the batteries negative (⊖) end first. Close the handset cover.



Note:

- When replacing batteries, remove the old batteries.



Preparation

Attention:



A nickel metal hydride battery that is recyclable powers the product you have purchased.


Please call 1-800-8-BATTERY (1-800-822-8837) for information on how to recycle this battery.

Battery charge


Place the handset on the base unit or charger for 7 hours before initial use.

- While charging, "Charging" is displayed. When the batteries are fully charged, "Charge completed" is displayed.

Base unit:



Charger*1:



*1 KX-TG8232

Note:

- It is normal for the handset to feel warm during charging.
- If you want to use the handset immediately, charge the batteries for at least 15 minutes.

- Clean the charge contacts of the handset, base unit, and charger with a soft, dry cloth once a month. Clean more often if the unit is subject to the exposure of grease, dust, or high humidity.
- When the batteries are empty, the entire display may go blank and "Charging" may not be displayed for about 10 minutes even if you place the handset on the base unit or charger.

Battery level

Battery icon	Battery level
	High
	Medium
	Low • When flashing: Needs to be charged.

Note:

- When the batteries need to be charged, the handset beeps intermittently during use.

Panasonic Ni-MH battery performance (supplied batteries)

Operation	Operating time
In continuous use	12 hours max.
In continuous standby mode	150 hours max.

Note:

- Battery operating time may be shortened over time depending on usage conditions and surrounding temperature.
- Battery power is consumed whenever the handset is off the base unit or charger, even when the handset is not in use.

Preparation

- After the handset is fully charged, displaying "charge completed", it may be left on the base unit or charger without any ill effect on the batteries.
- The battery level may not be displayed correctly or the entire display may go blank after you replace the batteries. In this case, place the handset on the base unit or charger and let it charge for 7 hours.

Screen saver mode

The backlight will turn off completely after 1 minute of inactivity if the handset is not on the base unit or charger. Press **[OFF]** to turn the display on again.

Symbols used in these operating instructions

Symbol	Meaning
[]	The words in the brackets indicate button names/ soft key names on the handset and base unit. Example: Unit keys: [RECALL] , [OFF] Soft keys: [CALL] , [REDIAL]
→	Proceed to the next operation.
" "	The words in quotations indicate the menu on the display. Example: "Alarm"

Symbol	Meaning
[▼]/[▲] : "	Push the handset joystick down or up to select the words in quotations. Example: [▼]/[▲] : "OFF"

Setting up the unit before use

Display language

You can select either "English" or "Español" as the display language. The default setting is "English".

- 1 **[MENU]** (center of joystick)
- 2 Select **[B]** by pushing the joystick in any direction. → **[SELECT]**
- 3 Push the joystick up or down to select "Change language". → **[SELECT]**
- 4 Push the joystick up or down to select the desired language.
- 5 Press down the center of the joystick to save.
- 6 **[OFF]**


Note:

- How to change from Spanish back to English:
 - ① **[MENU]** (center of joystick) → **[B]** → **[SELEC.]**
 - ② **[▼]/[▲]**: "Cambiar idioma" → **[SELEC.]**
 - ③ **[▼]/[▲]**: "English" → **[SAVE]** → **[OFF]**

Preparation


Voice guidance language

You can select either "English" or "Español" as the voice guidance language of the answering system (page 30). The default setting is "English".

- 1 **[MENU]** (center of joystick)
- 2 Select  by pushing the joystick in any direction. → **[SELECT]**
- 3 Push the joystick up or down to select "Settings". → **[SELECT]**
- 4 Push the joystick up or down to select "Voice prompt". → **[SELECT]**
- 5 Push the joystick up or down to select the desired language. → **[SAVE]** → **[OFF]**

Dialing mode


If you cannot make calls, change this setting according to your telephone line service. The default setting is "Tone".
"Tone": For tone dial service.
"Pulse": For rotary/pulse dial service.

- 1 **[MENU]** (center of joystick)
- 2 Select  by pushing the joystick in any direction. → **[SELECT]**
- 3 Push the joystick up or down to select "set tel line". → **[SELECT]**
- 4 Push the joystick up or down to select "set dial mode". → **[SELECT]**
- 5 Push the joystick up or down to select the desired setting. → **[SAVE]** → **[OFF]**

Date and time

Set the correct date and time so that:
 – You can use the alarm function (page 28).

– The unit will announce the day and time a message was recorded when you play back on the answering system (page 31).

- 1 **[MENU]** (center of joystick)
- 2 Select  by pushing the joystick in any direction. → **[SELECT]**
- 3 Push the joystick up or down to select "Date and time". → **[SELECT]**
- 4 Enter the current month, date, and year.
Example: August 15, 2007
[0][8] [1][5] [0][7]
- 5 Enter the current hour and minute (12-hour clock format).
Example: 9:30
[0][9] [3][0]
- 6 Press **[*]** to select "AM" or "PM".
- 7 **[SAVE]** → **[OFF]**

Note:

- When English is selected as the display language, 12-hour clock format is used. When Spanish is selected, 24-hour clock format is used.
- If you make a mistake when entering the date and time, push the joystick right, left, up, or down to move the cursor, then make the correction.
- The date and time may be incorrect after a power failure. In this case, set the date and time again.

Making/Answering Calls

Making calls

- 1 Dial the phone number.
 - To correct a digit, press **[CLEAR]**.
- 2 Press **[↶]**.
- 3 When you finish talking, press **[OFF]** or place the handset on the base unit or charger.

Using the speakerphone

- 1 Dial the phone number, and press **[☎]**.
 - Speak alternately with the other party.
- 2 When you finish talking, press **[OFF]**.

Note:

- For best performance, use the speakerphone in a quiet environment.
- To switch back to the receiver, press **[↶]**.

Adjusting the receiver/speaker volume

Push the joystick up or down repeatedly while talking.

Making a call using the redial list

The last 5 phone numbers dialed are stored in the redial list (each 48 digits max.).

- 1 **[REDIAL]** (right soft key)
- 2 **[▼]/[▲]**: Select the desired phone number.
- 3 **[↶]**

Erasing a number in the redial list

- 1 **[REDIAL]** (right soft key)

- 2 **[▼]/[▲]**: Select the desired phone number.
- 3 **[ERASE]**
- 4 **[▼]/[▲]**: "Yes" → **[SELECT]** → **[OFF]**

Note:

- Step 3 variation: **[MENU]** → **[▼]/[▲]**: "Erase" → **[SELECT]**

Erasing all numbers in the redial list

- 1 **[REDIAL]** (right soft key)
- 2 **[MENU]** → **[▼]/[▲]**: "Erase all" → **[SELECT]**
- 3 **[▼]/[▲]**: "Yes" → **[SELECT]**

PAUSE button (for PBX/long distance service users)

A pause is sometimes required when making calls using a PBX or long distance service. When storing a calling card access number and/or PIN in the phonebook, a pause is also needed (page 21).

For example, if you need to dial the line access number "9" when making outside calls with a PBX:

- 1 **[9]** → **[PAUSE]** → Dial the phone number.
- 2 **[↶]**

Note:

- A 3.5 second pause is inserted each time **[PAUSE]** is pressed. Press repeatedly to insert longer pauses.

Answering calls

- 1 Press **[↶]** or **[☎]** when the unit rings.
 - You can also answer the call by pressing any dial key from **[0]** to

Making/Answering Calls

[9], [*], or [#]. (Any key talk feature)

- When you finish talking, press **[OFF]** or place the handset on the base unit or charger.

Note:

- You can change the ringer tone (page 27). You can also adjust the handset ringer volume (page 27).

Auto talk

You can answer calls simply by lifting the handset off the base unit or charger. You do not need to press **[↶]**. To turn this feature on, see page 28.

Temporary ringer off

While the handset is ringing for a call, you can turn the ringer off temporarily by pressing **[⊘]** or **[OFF]**.

Useful features during a call

MUTE button

While mute is turned on, you can hear the other party, but the other party cannot hear you.

To mute your voice, press **[MUTE]**.

- To return to the conversation, press **[MUTE]** again or **[↶]**.

FLASH button

Pressing **[FLASH]** allows you to use special features of your host PBX such as transferring an extension call, or accessing optional telephone services.

Note:

- To change the flash time, see page 27.

For Call Waiting service users

To use Call Waiting, you must subscribe to the Call Waiting service of your service provider/telephone company. This feature allows you to receive calls while you are already talking on the phone. If you receive a call while on the phone, you will hear a Call Waiting tone. Please contact your service provider/telephone company for details and availability of this service in your area. Press **[CALL WAIT]** to answer the 2nd call.

- To switch between calls, press **[CALL WAIT]**.

Temporary tone dialing (for rotary/pulse service users)

You can temporarily switch the dialing mode to tone when you need to access touch-tone services (for example, answering services, telephone banking services, etc.).

Press **[*]** (TONE) before entering access numbers which require tone dialing.

Call share

This feature allows the handset to join an existing outside call.

To join the conversation, press **[↶]** when the other handset is on an outside call.

Note:

- A maximum of 3 parties (including 1 outside party) can join a conversation using 2 extensions.

Call privacy

Call privacy allows you to prevent other users from joining your conversations with outside callers. To allow other

Making/Answering Calls

users to join your conversations, leave this feature off. The default setting is "Off".

- 1** Press **[MENU]** during an outside call.
- 2** **[v]/[▲]**: "on" or "Off" → **[SELECT]**
 - When this feature is turned on, **PRIV** is displayed.

Note:

- This feature will turn off after you hang up the call.

Phonebook

Handset phonebook

The handset phonebook allows you to make calls without having to dial manually. You can add 50 names and phone numbers, assign each handset phonebook entry to the desired group.

Adding entries

- 1 **[M]** (left soft key)
- 2 **[ADD]**
- 3 Enter the party's name (16 characters max.). → **[OK]**
- 4 Enter the party's phone number (24 digits max.). → **[OK]**
- 5 **[v]/[▲]**: Select the desired group. → **[SELECT]**
- 6 **[v]/[▲]**: "save" → **[SELECT]**
 - To add other entries, repeat from step 3.
- 7 **[OFF]**

Note:

- Step 2 variation:
[MENU] → **[v]/[▲]**: "New entry"
 → **[SELECT]**

Character table for entering names

While entering characters, you can switch between uppercase and lowercase by pressing **[*]**.

Key	Character
[1]	Space # & ' () * , - . / 1
[2]	A B C 2
	a b c 2
[3]	D E F 3
	d e f 3

Key	Character
[4]	G H I 4
	g h i 4
[5]	J K L 5
	j k l 5
[6]	M N O 6
	m n o 6
[7]	P Q R S 7
	p q r s 7
[8]	T U V 8
	t u v 8
[9]	W X Y Z 9
	w x y z 9
[0]	Space 0

- To enter another character that is located on the same dial key, first push the joystick right to move the cursor to the next space.

Correcting a mistake

Push the joystick left or right to move the cursor to the character or number you want to erase, then press **[CLEAR]**. Enter the appropriate character or number.

- Press and hold **[CLEAR]** to erase all characters or numbers.

Group settings

Group setting can help you find entries in the handset phonebook quickly and easily. When adding an entry to the handset phonebook you can assign it to the desired group. You can change the names of groups assigned for handset phonebook entries ("Friends", "Family", etc.) and then search for handset phonebook entries by group. Additional

Phonebook

group setting features are available for Caller ID subscribers (page 23).

Changing group names

- 1 [] (left soft key) → [MENU]
- 2 [v]/[^]: "Group" → [SELECT]
- 3 [v]/[^]: Select the desired group. → [SELECT]
- 4 [v]/[^]: "Group name" → [SELECT]
- 5 Edit name (10 characters max.) → [SAVE] → [OFF]

Finding and calling a handset phonebook entry

Scrolling through all entries

- 1 [] (left soft key)
- 2 [v]/[^]: Select the desired entry.
- 3 []

Searching by first character (index search)

- 1 [] (left soft key)
- 2 Press the dial key ([0] – [9]) which contains the character you are searching for (see the character table, page 19).
 - Press the same dial key repeatedly to display the first entry corresponding to each letter located on that dial key.
 - If there is no entry corresponding to the character you selected, the next entry is displayed.
- 3 [v]/[^]: Scroll through the phonebook if necessary.
- 4 []

Searching by group

- 1 [] (left soft key) → [GROUP]
- 2 [v]/[^]: Select the desired group. → [SELECT]
 - If you select "All groups", the unit will end searching group.
- 3 [v]/[^]: Scroll through the phonebook if necessary.
- 4 []

Editing entries

- 1 Find the desired entry (page 20).
- 2 [EDIT]
- 3 Edit the name if necessary (see the character table, page 19). → [OK]
- 4 Edit the phone number if necessary (24 digits max.). → [OK]
- 5 [v]/[^]: Select the desired group. → [SELECT]
- 6 [v]/[^]: "Save" → [SELECT] → [OFF]

Note:

- Step 2 variation:
[MENU] → [v]/[^]: "Edit" → [SELECT]

Erasing entries

Erasing an entry

- 1 Find the desired entry (page 20).
- 2 [MENU]
- 3 [v]/[^]: "Erase" → [SELECT]
- 4 [v]/[^]: "Yes" → [SELECT] → [OFF]

Erasing all entries

- 1 [] (left soft key)
- 2 [MENU]

Phonebook

- 3 **[▼]/[▲]**: "Erase all" → **[SELECT]**
- 4 **[▼]/[▲]**: "Yes" → **[SELECT]**
- 5 **[▼]/[▲]**: "Yes" → **[SELECT]** → **[OFF]**

One touch dial

Assigning an entry in the handset phonebook to a one touch dial key

Dial keys **[1]** to **[9]** can each be used as a one touch dial key, allowing you to dial a number from the handset phonebook by simply pressing a dial key.

- 1 Find the desired entry (page 20). → **[MENU]**
- 2 **[▼]/[▲]**: "1-touch dial" → **[SELECT]**
- 3 **[▼]/[▲]**: Select the desired dial key number. → **[SELECT]**
 - When the dial key is already used as a one touch dial key, "*" is displayed next to the dial key number. If you select this dial key, you can overwrite the previous assignment.
- 4 **[▼]/[▲]**: "save" → **[SELECT]** → **[OFF]**

Making a call using a one touch dial key

- 1 Press and hold the desired one touch dial key (**[1]** to **[9]**).
 - You can view other one touch dial assignments by pushing the joystick up or down.
- 2 **[↶]**

Canceling a one touch dial assignment

- 1 Press and hold the desired one touch dial key (**[1]** to **[9]**).
- 2 **[ERASE]**
- 3 **[▼]/[▲]**: "Yes" → **[SELECT]** → **[OFF]**

Note:

- Step 2 variation:
[MENU] → **[▼]/[▲]**: "Erase" → **[SELECT]**

Chain dial

This feature allows you to dial phone numbers in the handset phonebook while you are on a call. This feature can be used, for example, to dial a calling card access number or bank account PIN that you have stored in the handset phonebook, without having to dial manually.

- 1 During an outside call, press **[📞]**.
- 2 **[▼]/[▲]**: Select the desired entry.
- 3 Press **[CALL]** to dial the number.

Note:

- When storing a calling card access number and your PIN in the phonebook as one phonebook entry, press **[PAUSE]** to add pauses after the number and PIN as necessary (page 16).
- If you have rotary/pulse service, you need to press **[✳]** before pressing **[📞]** in step 1 to change the dialing mode temporarily to tone.

Phonebook

Copying handset phonebook entries

You can copy handset phonebook entries to the handset phonebook of another compatible Panasonic handset.

Note:

- Group settings for phonebook entries are not copied.

Copying an entry

- 1 Find the desired entry (page 20). → **[MENU]**
- 2 **[▼]/[▲]**: "Copy" → **[SELECT]**
- 3 Select the handset to copy to by pressing the desired handset number (**[1]** – **[6]**).
 - When an entry has been copied, "Completed" is displayed.
 - To continue copying another entry:
[▼]/[▲]: "Yes" → **[SELECT]** → Find the desired entry. → **[OK]**
- 4 **[OFF]**

Copying all entries

- 1 **[☰]** (left soft key) → **[MENU]**
- 2 **[▼]/[▲]**: "Copy all" → **[SELECT]**
- 3 Select the handset to copy to by pressing the desired handset number (**[1]** – **[6]**).
 - When all entries have been copied, "Completed" is displayed.
- 4 **[OFF]**

Caller ID Service

Using Caller ID service

Important:

- This unit is Caller ID compatible. To use Caller ID features, you must subscribe to Caller ID service. Consult your service provider/telephone company for details.

Caller ID features

When an outside call is being received, the calling party's name and phone number are displayed.

Caller information for the last 50 callers is logged in the caller list by the most recent call to the oldest.

- Generally caller information is displayed from the 2nd ring.
- If the unit cannot receive caller information, the following is displayed:
 - “**Out of area**”: The caller dialed from an area which does not provide Caller ID service.
 - “**Private caller**”: The caller requested not to send caller information.
 - “**Long distance**”: The caller called you long distance.
- If the unit is connected to a PBX system, caller information may not be received properly. Consult your PBX supplier.

Missed calls

If a call is not answered, the unit treats the call as a missed call. The display shows “**missed call**”. This lets you know if you should view the caller list to see who called while you were out.

Custom name display

When the Caller ID number is received and it matches a phone number stored

in the phonebook, the stored name from the phonebook is displayed and logged in the caller list.

Call Waiting Caller ID display

If you subscribe to both Caller ID and Call Waiting with Caller ID services, the 2nd caller's information is displayed after you hear a Call Waiting tone.

Press **[CALL WAIT]** to answer the 2nd call.

- To switch between calls, press **[CALL WAIT]**.

Note:

- Please contact your service provider/telephone company for details and availability of this service in your area.

Group settings for handset phonebook

Group settings can help you identify who is calling by using different ringer tones and display colors for different groups of callers. When adding an entry to the handset phonebook you can assign it to desired group (page 19). When a call is received from a caller assigned to a group, the group's display color and ringer tone you selected are used.

Changing group ringer tones

If you select “**No ringer ID**”, the unit will use the external ringer tone you set on page 27 when calls from this group are received. The default is “**No ringer ID**”.

- 1 **[☰]** (left soft key) → **[MENU]**
- 2 **[▼]/[▲]**: “**Group**” → **[SELECT]**
- 3 **[▼]/[▲]**: Select a group. → **[SELECT]**

Caller ID Service

4 [▼]/[▲]: Select the current setting of the group ringer tone. → [SELECT]

5 [▼]/[▲]: Select the desired ringer tone. → [SAVE] → [OFF]

Changing group display colors

If you select "No color ID", the unit will use the display color you set on page 27 when calls from this group are received. The default is "No color ID".

1 [M] (left soft key) → [MENU]

2 [▼]/[▲]: "Group" → [SELECT]

3 [▼]/[▲]: Select a group. → [SELECT]

4 [▼]/[▲]: Select the current setting of the group color. → [SELECT]

5 [▼]/[▲]: Select the desired color. → [SAVE] → [OFF]

Caller list

Viewing the caller list and calling back

1 [MENU] (center of joystick) → → [SELECT]

2 Push the joystick down to search from the most recent call, or push the joystick up to search from the oldest call.

3 To call back, press [↩].
To exit, press [OFF].

Note:

- If the item has already been viewed or answered, "✓" is displayed, even if it was viewed or answered using another handset.

Editing a caller's phone number before calling back

You can edit a phone number in the caller list by removing its area code and/or the long distance code "1".

1 [MENU] (center of joystick) → → [SELECT]

2 [▼]/[▲]: Select the desired item. → [EDIT]

3 Press [EDIT] repeatedly until the phone number is shown in the desired format.

① Local phone number

Ex:

② Area code – Local phone number

Ex:

③ 1 – Area code – Local phone number

Ex:

4 [↩]

Caller ID number auto edit feature

Once you call back an edited number, the unit will remember the Area Code and Format of the Edited Number. Next time when someone calls from the same Area Code, caller information will be customized by the unit as follows:

- When the call is being received, the Caller ID number will be displayed in the same Format as the Edited Number.
- After the call is ended, the phone number of the caller, when reviewed from the Caller list, will be displayed in the same Format as the Edited Number.

For example, you can use this feature to set the unit to ignore the area code of callers in your area code, so that you can call these local numbers using caller information without dialing the area code.

Caller ID Service

To activate this feature, you must edit an item in the caller list, then call that number. After that, phone numbers from that caller's area code are edited automatically.

This feature can be turned on or off (page 28).

Note:

- Phone numbers from the 4 most recently edited area codes are automatically edited.
- If you move to another area, you can turn this feature off to erase previously edited area codes. To use this feature again, turn it on and reprogram the area codes you want to edit once again.

Erasing selected caller information

- 1 **[MENU]** (center of joystick) → →) → **[SELECT]**
- 2 **[▼]/[▲]**: Select the desired item.
- 3 **[ERASE]**
- 4 **[▼]/[▲]**: "Yes" → **[SELECT]** → **[OFF]**

Erasing all caller information

- 1 **[MENU]** (center of joystick) → →) → **[SELECT]**
- 2 **[ERASE]**
- 3 **[▼]/[▲]**: "Yes" → **[SELECT]**

Storing caller information into the phonebook

- 1 **[MENU]** (center of joystick) → →) → **[SELECT]**
- 2 **[▼]/[▲]**: Select the desired item.
 - To edit the number, press **[EDIT]** repeatedly until the phone number is shown in the desired format.

3 **[SAVE]**

4 Edit the name if necessary (see the character table, page 19). → **[OK]**

5 Edit the phone number if necessary. → **[OK]**

6 **[▼]/[▲]**: Select the desired group. → **[SELECT]**

7 **[▼]/[▲]**: "save" → **[SELECT]** → **[OFF]**

Programming

Programmable settings

You can customize the unit by programming the following features using the handset.

Programming by scrolling through the display menus



- 1 **[MENU]** (center of joystick)
- 2 Select "Menu icon" by pushing the joystick in any direction. → **[SELECT]**
- 3 Push the joystick up or down to select the desired item in the sub-menu. → **[SELECT]**
 - In some cases, you may need to select from a second sub-menu. → **[SELECT]**
- 4 Push the joystick up or down to select the desired setting then press **[SAVE]**.
 - This step may vary depending on the feature being programmed.
 - To exit the operation, press **[OFF]**.

Note:



- In the following table, < > indicates the default setting.
- The current item or setting is highlighted on the display.

Main menu	Sub-menu 1	Sub-menu 2	Page
View Caller ID →	–	–	24
Display settings ☰	Wallpaper <Wallpaper1 >	–	–
	Display color <Color1>	–	–
	Change language <English>	–	14
	Contrast <Contrast 3>	–	–
Set date & time 🕒	Date and time ^{*1}	–	15
	Alarm <Off>	–	28
	Time adjustment ^{*1, *2} <Caller ID[auto]>	–	–
Answering device 📞	Play new msg.	–	32
	Play all msg.	–	32
	Record greeting ^{*1}	–	31

Programming

Main menu	Sub-menu 1	Sub-menu 2	Page
Answering device 	Answer on ^{*1} Answer off ^{*1} <Answer on>	-	30
	Play greeting	-	31
	Erase message	Erase all ^{*1}	32
		Erase greeting ^{*1}	31
	Settings	Remote code ^{*1} <111>	34
		Ring count ^{*1} <4 rings>	35
		Recording time ^{*1} <3 min>	35
		Call screening ^{*1} <On>	35
		Voice prompt ^{*1} <English>	15
	Initial settings 	Ringer settings	Ringer volume <Level 6> ^{*3}
Ringer tone ^{*4, *5, *6} <Tone 1>			-
Display settings		Wallpaper <Wallpaper1 >	-
		Display color <Color1>	-
		Change language <English>	14
		Contrast <Contrast 3>	-
Registration		HS registration (Handset registration)	38
		Deregistration	38
Set tel line		Set dial mode ^{*1} <Tone>	15
		Set flash time <700 ms> ^{*1, *7}	17


Programming

Main menu	Sub-menu 1	Sub-menu 2	Page
Initial settings 	Other settings	Key tone ^{*8} <On>	–
		Auto talk ^{*9} <Off>	17
		Caller ID edit <On>	24
Customer support 	–	–	29

- *1 If you program these settings using one of the handsets, you do not need to program the same item using another handset.
- *2 This feature allows the unit to automatically adjust the date and time setting when caller information is received. To use this feature, set the date and time first.
- *3 When the ringer volume is turned off, \mathcal{R} is displayed and the handset does not ring for outside calls.
However even when the ringer volume is turned off, the handset rings:
– at the minimum level for alarm and intercom calls
– at the maximum level for paging
- *4 If you subscribe to a distinctive ring service (such as IDENT-A-RING), select a tone (tone 1 to 5). If you select a melody, you cannot distinguish lines by their ringers.
- *5 The preset melodies in this product are used with permission of © 2006 Copyrights Vision Inc.
- *6 If you select one of the melody ringer tones, the ringer tone will continue to sound for several seconds if the caller hangs up before you answer. You may hear a dial tone or no one on the line when you answer a call.
- *7 The flash time depends on your telephone exchange or host PBX. Consult your PBX supplier if necessary. The setting should stay at “700 ms” unless pressing **[FLASH]** fails to pick up the call waiting call.
- *8 Turn this feature off if you prefer not to hear key tones while you are dialing or pressing any keys, including confirmation tones and error tones.
- *9 If you subscribe to Caller ID service and want to view the caller's information after lifting up the handset to answer a call, turn off this feature.

Alarm

An alarm will sound at the set time for 3 minutes in two different alarm modes: Once or Daily. Set the date and time beforehand (page 15).

- 1 **[MENU]** (center of joystick) →  → **[SELECT]**
- 2 **[v]/[▲]**: “Alarm” → **[SELECT]**
- 3 **[v]/[▲]**: Select the desired alarm mode. → **[SELECT]**

Programming


Off	Turns alarm off. Press [SELECT] again, then press [OFF] to exit.
Once	The alarm sounds once at the set time. Enter the desired month and date.
Daily	An alarm sounds daily at the set time.

4 Set the desired time. → **[OK]**

5 **[▼]/[▲]**: Select the desired ringer tone. → **[SELECT]**

- We recommend selecting a different ringer tone from outside call.

6 **[▼]/[▲]**: "save" → **[SELECT]** → **[OFF]**


- When the alarm is set,  is displayed.

Note:

- To stop the alarm, press any dial key or place the handset on the base unit or charger.
- When the handset is in use, the alarm will not sound until the handset is in standby mode.
- If you select "once", the setting will change to "off" after the alarm sounds.

Customer support

The handset can display the Internet address where you can download the operating instructions or get further information for this product by using your computer.

1 **[MENU]** (center of joystick) →  → **[SELECT]**

2 **[OFF]**

Answering System

Answering system

The answering system can answer and record calls for you when you are unavailable to answer the phone.

Important:

- Only 1 person can access the answering system (listen to messages, record a greeting message, etc.) at a time.
- When callers leave messages, the unit records the day and time of each message. Make sure the date and time have been correctly set (page 15).

Memory capacity

The total recording capacity (including your greeting message and caller messages) is about 18 minutes. A maximum of 64 messages can be recorded.

Note:

- If message memory becomes full:
 - “**Messages full**” is shown on the handset display
 - the Message indicator on the base unit flashes rapidly
- When the message memory becomes full, the greeting message is different depending on your situation:
 - If you use the prerecorded greeting message, the unit automatically switches to another prerecorded greeting message asking callers to call again later.
 - If you recorded your own greeting message, the same message is still announced to callers even though their messages are not recorded.

Turning the answering system on/off

Using the base unit

Press **[ON]** (ANSWER ON) to turn on/off the answering system.

- When the answering system is turned on, the ANSWER ON indicator lights up.

Using the handset

- 1 **[MENU]** (center of joystick) → **[OK]**
→ **[SELECT]**
- 2 **[V]/[A]**: “Answer on” or “Answer off” → **[SELECT]** → **[OFF]**

Call screening

While a caller is leaving a message, you can listen to the call through the handset’s speaker.

You can answer the call by pressing **[hook]** on the handset.

Note:

- To temporarily mute call screening on the handset, press **[SILENCE]**. To screen again in the call, push the joystick up accordingly.
- To turn this feature off, see page 35.


Greeting message

When the unit answers a call, callers are greeted by a greeting message. You can record your own greeting message or use a pre-recorded greeting message.

Answering System

Recording your greeting message


You can record your own greeting message (2 minutes and 30 seconds max.).

- 1 **[MENU]** (center of joystick) →  → **[SELECT]**
- 2 **[▼]/[▲]**: "Record greeting" → **[SELECT]**
- 3 Hold the handset about 20 cm (8 inches) away and speak clearly into the microphone.
- 4 To stop recording, press **[STOP]**.
- 5 **[OFF]**

Using a pre-recorded greeting message

If you erase or do not record your own greeting message, the unit plays a pre-recorded greeting message for callers and asks them to leave messages.

Playing back the greeting message


- 1 **[MENU]** (center of joystick) →  → **[SELECT]**
- 2 **[▼]/[▲]**: "Play greeting" → **[SELECT]** → **[OFF]**

Note:

- You can erase your own greeting message by pressing **[ERASE]** during playback.

Erasing your greeting message

If you erase your own greeting message, the unit will play a pre-recorded greeting message for callers.

- 1 **[MENU]** (center of joystick) →  → **[SELECT]**
- 2 **[▼]/[▲]**: "Erase message" → **[SELECT]**
- 3 **[▼]/[▲]**: "Erase greeting" → **[SELECT]**

- 4 **[▼]/[▲]**: "Yes" → **[SELECT]** → **[OFF]**

Listening to messages using the base unit

When new messages have been recorded, the Message indicator on the base unit flashes.

Press **[▶]** (Message).

- If new messages have been recorded, the base unit plays back new messages.
- If there are no new messages, the base unit plays back all messages.

Note:

- When the Message indicator on the base unit flashes rapidly, the message memory is full ("Memory capacity", page 30).

Operating the answering system

Key	Operation
[▲] or [▼]	Adjust the speaker volume (during playback)
[◀◀]	Repeat message (during playback)*1
[▶▶]	Skip message (during playback)
[■] (STOP)	Stop playback
[X] (ERASE)	Erase currently playing message

*1 If pressed within the first 5 seconds of a message, the previous message is played.

Erasing all messages

Press **[X]** (ERASE) 2 times while the unit is not being used.

Answering System

Listening to messages using the handset

When new messages have been recorded, "New message" is displayed.

- 1 **[MENU]** (center of joystick) → **[OK]** → **[SELECT]**
- 2 **[▼]/[▲]**: "Play new msg." or "Play all msg." → **[SELECT]**
- 3 When finished, press **[OFF]**.

Note:

- To switch to the receiver, press **[↶]**.

Calling back (Caller ID subscribers only)

If caller information was received for the call, you can call the caller back while listening to a message.

- 1 Press **[MENU]** during playback.
- 2 **[▼]/[▲]**: "Edit & Call" → **[SELECT]**
 - Press **[EDIT]** repeatedly until the phone number is shown in the desired format.
- 3 **[CALL]**

Erasing all messages

- 1 **[MENU]** (center of joystick) → **[OK]** → **[SELECT]**
- 2 **[▼]/[▲]**: "Erase message" → **[SELECT]**
- 3 **[▼]/[▲]**: "Erase all" → **[SELECT]**
- 4 **[▼]/[▲]**: "Yes" → **[SELECT]** → **[OFF]**

Operating the answering system

You can also operate the answering system by pressing dial keys on the handset.

To use the following commands:

- [MENU]** (center of joystick) → **[OK]** → **[SELECT]**

Key	Operation
Pushing the joystick up or down	Adjust the receiver/speaker volume (during playback)
[1] or push the joystick left	Repeat message (during playback)*1
[2] or push the joystick right	Skip message (during playback)
[3]	Enter the "settings" menu
[4]	Play new messages
[5]	Play all messages
[6]	Play greeting message
[7][6]	Record greeting message
[8]	Turn answering system on
[9]	Stop (recording, playback)
[0]	Turn answering system off
[*][4]**2	Erase currently playing message
[*][5]	Erase all messages
[*][6]	Erase greeting message

Answering System

*1 If pressed within the first 5 seconds of a message, the previous message is played.

*2 You can also erase as follows:
[ERASE] → **[▼]/[▲]**: "Yes" → **[SELECT]**

Remote operation

Using a touch-tone phone, you can call your phone number from outside and access the unit to listen to messages or change answering system settings. The unit's voice guidance will prompt you to press certain dial keys to perform different operations.

Important:

- In order to operate the answering system remotely, you must first set a remote access code (page 34). This code must be entered each time you operate the answering system remotely.

Using the answering system remotely

- 1 Dial your phone number from a touch-tone phone.
- 2 After the greeting message starts, enter your remote access code (page 34).
 - The unit announces the number of new messages.
 - The voice guidance informs you of the available commands. The announcements are different depending on the voice guidance language setting (page 15).
- 3 Control the unit using remote commands (page 34).
- 4 When finished, hang up.

Voice guidance

When the English voice guidance is selected

During remote operation, the unit's voice guidance starts and prompts you to press **[1]** to perform a specific operation, or press **[2]** to listen to more available operations. Operations are presented by voice guidance in the following order:

- Play back all messages
- Play back new messages
- Record a message
- Erase all messages
- Record a greeting message

Note:

- If you do not press any dial keys within 10 seconds after a voice guidance prompt, the unit disconnects your call.

When the Spanish voice guidance is selected

To start the voice guidance, press **[9]**. The voice guidance announces the available remote commands (page 34). See the Spanish Quick Guide for details.

Note:

- If you do not press any dial keys within 10 seconds after a voice guidance prompt, the unit disconnects your call.

Remote commands

You can press dial keys to access certain answering system functions without waiting for the voice guidance to prompt you.

Answering System

Key	Operation
[1]	Repeat message (during playback) ^{*1}
[2]	Skip message (during playback)
[4]	Play new messages
[5]	Play all messages
[6]	Play greeting message
[7]	Record greeting message
[9]	Stop recording Stop playback ^{*2} Start voice guidance ^{*3}
[0]	Turn answering system off
[*][4]	Erase currently playing message
[*][5]	Erase all messages
[*][6]	Erase greeting message (during greeting message playback)
[*][#]	End remote operation (or hang up)

*1 If pressed within the first 5 seconds of a message, the previous message is played.

*2 For English voice guidance only
 • To resume operation, enter a remote command within 3 seconds, or the voice guidance starts.

*3 For Spanish voice guidance only

Turning on the answering system remotely

If the answering system is off, you can turn it on remotely.

- 1 Dial your phone number from a touch-tone phone.
- 2 Let the phone ring 15 times.
 - A long beep will be heard.
- 3 Enter your remote access code within 10 seconds after the long beep.
 - The greeting message is played back.
 - You can hang up, or enter your remote access code again and begin remote operation (page 33).


Skipping the greeting message to leave a message

You can leave a message just as any outside caller can. Call your phone number. When the answering system picks up, press [*] to skip the greeting message and record your message after the beep.

Answering system settings

Remote access code

A 3-digit remote access code must be entered when operating the answering system remotely. This code prevents unauthorized parties from listening to your messages remotely. The default setting is "111".

- 1 [MENU] (center of joystick) →  → [SELECT]
- 2 [▼]/[▲]: "Settings" → [SELECT]
- 3 [▼]/[▲]: "Remote code" → [SELECT]
- 4 Enter the desired 3-digit remote access code. → [SAVE] → [OFF]


Answering System

Ring count

You can change the number of times the phone rings before the unit answers calls. You can select 2 to 7 rings, or "Toll saver".

The default setting is "4 rings".

"Toll saver": The unit's answering system answers at the end of 2nd ring when new messages have been recorded, or at the end of 4th ring when there are no new messages. If you call your phone from outside to listen to new messages (page 33), you will know that there are no new messages when the phone rings for the 3rd time. You can then hang up without being charged for the call.

- 1 **[MENU]** (center of joystick) →  → **[SELECT]**
- 2 **[▼]/[▲]**: "Settings" → **[SELECT]**
- 3 **[▼]/[▲]**: "Ring count" → **[SELECT]**
- 4 **[▼]/[▲]**: Select the desired setting.
- 5 **[SAVE]** → **[OFF]**

For Voice Mail service subscribers

If you subscribe to a flat-rate service package that includes Caller ID, Call Waiting, Voice Mail, and unlimited local/regional/long distance calls, please note the following:


- To use the Voice Mail service provided by your service provider/telephone company rather than the unit's answering system, turn off the answering system (page 30).
- To use this unit's answering system rather than the Voice Mail service provided by your service provider/telephone company, please contact your service provider/telephone company to deactivate your Voice Mail service.

If your service provider/telephone company cannot do this:

- Set this unit's "Ring count" setting so that this unit's answering system answers calls before the Voice Mail service of your service provider/telephone company does. It is necessary to check the ring count required to activate the Voice Mail service provided by your service provider/telephone company before changing this setting.
- Change the ring count of the Voice Mail service so that the answering system can answer the call first. To do so, consult your service provider/telephone company.


Caller's recording time

You can change the maximum message recording time allotted to each caller. The default setting is "3 min".

- 1 **[MENU]** (center of joystick) →  → **[SELECT]**
- 2 **[▼]/[▲]**: "Settings" → **[SELECT]**
- 3 **[▼]/[▲]**: "Recording time" → **[SELECT]**
- 4 **[▼]/[▲]**: Select the desired setting.
- 5 **[SAVE]** → **[OFF]**

Call screening

You can set the call screening feature "On" or "Off". For details, see page 30. The default setting is "On".

- 1 **[MENU]** (center of joystick) →  → **[SELECT]**
- 2 **[▼]/[▲]**: "Settings" → **[SELECT]**
- 3 **[▼]/[▲]**: "Call screening" → **[SELECT]**
- 4 **[▼]/[▲]**: Select the desired setting.
- 5 **[SAVE]** → **[OFF]**

Voice Mail Service

Using Voice Mail service

Voice Mail is an automatic answering service offered by your service provider/telephone company. After you subscribe to this service, the service provider/telephone company's Voice Mail system will answer calls for you when you are unavailable to answer the phone or when your line is busy. Messages are recorded by the service provider/telephone company, not your telephone.

Important:

- To use the Voice Mail service provided by your service provider/telephone company rather than the unit's answering system, turn off the answering system (page 30). For details, see page 35.

Voice Mail message indication

When you have new messages, "New Voice Mail" is displayed on the handset.

- In order to listen to your Voice Mail messages, you must dial your service provider/telephone company's Voice Mail access number.

Note:

- If the handset still indicates there are new messages even after you have listened to new messages, turn it off by pressing and holding **[CLEAR]** until the handset beeps.
- The indication of "New Voice Mail" may not display properly depending on availability of your service provider/telephone company. Please contact your service provider/telephone company for details.

Multi-unit Operation

Operating additional handsets

Additional handsets

Up to 6 handsets can be registered to the base unit.

Important:

- See page 4 for information on the available model.
- Additional handsets will give you the freedom to, for example, have an intercom call with another handset while a third handset is on an outside call.

Intercom

Intercom calls can be made between handsets.

Note:

- If you receive an outside call while talking on the intercom, you hear 2 tones. To answer the call, press **[OFF]**, then press **[↶]**.
- When paging a unit for an intercom call, the paged unit beeps for 1 minute.

Making an intercom call

- 1 [INTERCOM]**
- Select the handset you want to page by pressing the desired handset number (**[1]** – **[6]**).
 - To stop paging, press **[OFF]**.
- When you finish talking, press **[OFF]**.

Answering an intercom call

- Press **[↶]** or **[↷]** to answer the page.
- When you finish talking, press **[OFF]**.

Handset locator

You can locate a misplaced handset by paging it.

- 1 Base unit:**
[•••] (LOCATOR)
 - The handset beeps for 1 minute.
- To stop paging:
Base unit:
Press **[•••]** (LOCATOR).
Handset:
Press **[OFF]**.

Transferring calls between handsets, conference calls

Outside calls can be transferred between 2 handsets. 2 handsets can have a conference call with an outside party.

- During an outside call, press **[TRANSFER]** to put the call on hold.
- Select the handset you want to transfer to by pressing the desired handset number (**[1]** – **[6]**).
- Wait for the paged party to answer.
 - If the paged party does not answer, press **[↶]** to return to the outside call.
- To complete the transfer:**
Press **[OFF]**.
 - The outside call is being routed to the handset.

Multi-unit Operation

To establish a conference call:

Press **[CONF]**.

- To leave the conference, press **[OFF]**. The other parties can continue the conversation.

Answering transferred calls

Press **[↶]** to answer the page.

- After the paging party disconnects, you can talk to the outside caller.

Transferring a call without speaking to the other handset user

- 1 During an outside call, press **[TRANSFER]**. → Press the desired handset number.
 - **[↶]** flashes to indicate the outside call is on hold.

2 [OFF]

- The outside call rings at the other handset.

Note:

- If the other handset user does not answer the call within 1 minute, the call will ring at your handset again.

Registering a handset to a base unit

The supplied handset and base unit are pre-registered. If for some reason the handset is not registered to the base unit (for example, **Y** flashes even when the handset is near the base unit), register the handset.

- 1 **[MENU]** (center of joystick) → **[?]** → **[SELECT]**

- 2 **[▼]/[▲]**: "Registration" → **[SELECT]**

- 3 **[▼]/[▲]**: "HS registration" → **[SELECT]**

4 Base unit:

Press and hold **[•••]** (LOCATOR) for about 5 seconds, until the registration tone sounds.

- If all registered handsets start ringing, press **[•••]** (LOCATOR) to stop, then repeat this step.
- After pressing **[•••]** (LOCATOR), the rest of this procedure must be completed within 1 minute and 30 seconds.

5 Handset:

Press **[OK]**, then wait until a long beep sounds and **Y** stops flashing.

- When the handset has been registered successfully, **Y** will stop flashing. If the key tone is turned on (page 28), a confirmation tone will be heard.

Deregistering a handset

A handset can cancel its own registration (or the registration of another handset) that is stored in the base unit. This will allow the handset to end its wireless connection with the system.

- 1 **[MENU]** (center of joystick) → **[?]** → **[SELECT]**

- 2 **[▼]/[▲]**: "Registration" → **[SELECT]**

- 3 **[▼]/[▲]**: "Deregistration" → **[SELECT]**

- 4 **[3][3][5]** → **[OK]**

- The numbers of all handsets registered to the base unit are displayed.

- 5 Select the handset(s) you want to cancel, by pressing the desired handset number (**[1]** - **[6]**). → **[OK]**

- The selected handset number(s) flashes.

Multi-unit Operation


- To cancel a selected handset number, press the number again. The number stops flashing.
- 6** [▼]/[▲]: "Yes" → [SELECT]
- A long beep will sound as each handset number disappears.
- 7** After "Deregistered" is displayed, press [OFF].

Useful Information


Belt clip

You can hang the handset on your belt or pocket using the supplied belt clip.

To attach the belt clip




To remove the belt clip



Headset (optional)

Connecting a headset to the handset allows hands-free phone conversations. We recommend using the Panasonic headset noted on page 4.



- Headset shown is KX-TCA86.

Useful Information

Error messages

If the unit detects a problem, one of the following messages is shown on the display.

Display message	Cause/solution
Busy	<ul style="list-style-type: none"> • The called handset is in use. • The handset you are calling is too far from the base unit. • There is no handset registered to the base unit matching the extension number you entered. • Other units are in use and the system is busy. Try again later.
Error!!	<ul style="list-style-type: none"> • Recording was too short. Try again.
Failed	<ul style="list-style-type: none"> • Phonebook copy failed. Confirm the other handset (the receiver) is in standby mode and try again.
Incomplete	<ul style="list-style-type: none"> • The receiver's phonebook memory is full. Erase the unnecessary phonebook entries from the other handset (the receiver) and try again.
Memory full	<ul style="list-style-type: none"> • The handset's phonebook memory is full. Erase unnecessary entries (page 20).
Messages full	<ul style="list-style-type: none"> • Message memory becomes full. Erase unnecessary messages (page 31).
No items stored	<ul style="list-style-type: none"> • Your phonebook, caller list or redial list is empty.
No link to base. Move closer to base, try again.	<ul style="list-style-type: none"> • The handset has lost communication with the base unit. Move closer to the base unit and try again. • Unplug the base unit's AC adaptor to reset the unit. Reconnect the adaptor and try again. • The handset's registration may have been canceled. Re-register the handset (page 38).
Please lift up and try again.	<ul style="list-style-type: none"> • A handset button was pressed while the handset was on the base unit or charger. Lift the handset and press the button again.
You must first subscribe to Caller ID.	<ul style="list-style-type: none"> • You must subscribe to Caller ID service. Once you receive caller information after subscribing to Caller ID service, this message will not be displayed.

Useful Information

Troubleshooting

If you still have difficulties after following the instructions in this section, disconnect the base unit AC adaptor, then reconnect the base unit AC adaptor.

General use

Problem	Cause/solution
The unit does not work.	<ul style="list-style-type: none"> • Make sure the batteries are installed correctly and fully charged (page 12). • Check the connections (page 11). • Unplug the base unit's AC adaptor to reset the unit. Reconnect the adaptor and try again. • The handset has not been registered to the base unit. Register the handset (page 38).
I cannot hear a dial tone.	<ul style="list-style-type: none"> • The base unit AC adaptor or telephone line cord is not connected. Check the connections. • If you are using a splitter to connect the unit, remove the splitter and connect the unit to the wall socket directly. If the unit operates properly, check the splitter. • Disconnect the unit from the telephone line and connect a known working telephone. If the working telephone operates properly, contact our service personnel to have the unit repaired. If the working telephone does not operate properly, contact your service provider/telephone company.
I do not know how to erase "missed call" from the display.	<ul style="list-style-type: none"> • There are unviewed missed calls remaining. View them using the following method. <ol style="list-style-type: none"> 1 [MENU] (center of joystick) → → [SELECT] 2 Push the joystick down to search from the most recent call, or push the joystick up to search from the oldest call.



Programmable settings

Problem	Cause/solution
I have changed the display language to a language I cannot read.	<ul style="list-style-type: none"> • Change the display language (page 14).

Useful Information

Problem	Cause/solution
I cannot program items.	<ul style="list-style-type: none"> Programming is not possible while either the base unit or another handset is being used. Try again later.
While programming, the handset starts to ring.	<ul style="list-style-type: none"> A call is being received. Answer the call and start again after hanging up.
I cannot register a handset to a base unit.	<ul style="list-style-type: none"> The maximum number of handsets (6) is already registered to the base unit. Cancel unused handset registrations from the base unit (page 38). Place the handset and the base unit away from other electrical appliances.

Battery recharge

Problem	Cause/solution
The batteries should be charging but the battery icon does not change.	<ul style="list-style-type: none"> Clean the charge contacts and charge again (page 13).
The handset beeps intermittently and/or  flashes.	<ul style="list-style-type: none"> Fully charge the batteries (page 13).
I fully charged the batteries, but  still flashes.	<ul style="list-style-type: none"> Clean the charge contacts and charge again (page 13). It is time to replace the batteries (page 12).
I fully charged the batteries, but the operating time seems to be short.	<ul style="list-style-type: none"> Wipe the battery ends (\oplus, \ominus) and the unit contacts with a dry cloth.
The handset display is blank.	<ul style="list-style-type: none"> The handset is in screen saver mode (page 14). Press [OFF] to activate the handset display again. Confirm that the batteries are properly installed. Fully charge the batteries (page 13).

Useful Information

Making/answering calls, intercom

Problem	Cause/solution
⚡ is flashing.	<ul style="list-style-type: none"> • The handset is not registered to the base unit. Register it (page 38). • The handset is too far from the base unit. Move closer. • The base unit AC adaptor is not connected. Check the connections. • You are using the handset or base unit in an area with high electrical interference. Place the handset and base unit away from interference sources, such as antennas and mobile phones.
⚡ is displayed, but I cannot make a call.	<ul style="list-style-type: none"> • The handset and base unit could not communicate for some reason, such as interference from other electrical appliances. Perform the following: <ul style="list-style-type: none"> – Move the handset and base unit away from other electrical appliances. – Move closer to the base unit.
Static is heard, sound cuts in and out. Interference from other electrical units.	<ul style="list-style-type: none"> • Place the handset and the base unit away from other electrical appliances. • Move closer to the base unit. • If your unit is connected to a telephone line with DSL service, we recommend connecting a noise filter between the base unit and the telephone line jack. Contact your DSL provider for details.
Noise is heard during a call.	<ul style="list-style-type: none"> • You are using the handset or base unit in an area with high electrical interference. Place the handset and base unit away from interference sources, such as antennas and mobile phones.
The handset does not ring.	<ul style="list-style-type: none"> • The ringer volume is turned off. Adjust the ringer volume (page 27).
I cannot make a call.	<ul style="list-style-type: none"> • The dialing mode may be set incorrectly. Change the setting (page 15). • Another handset is in use or the answering system is being used. Wait and try again later.
I cannot have a conversation using the headset.	<ul style="list-style-type: none"> • Make sure that an optional headset is connected properly (page 40).
I cannot make long distance calls.	<ul style="list-style-type: none"> • Make sure that you have long distance service.

Useful Information

Problem	Cause/solution
I cannot page the handset.	<ul style="list-style-type: none"> • The called handset is too far from the base unit. • The called handset is in use. Try again later.

Caller ID

Problem	Cause/solution
The handset does not display the caller's name and/or phone number.	<ul style="list-style-type: none"> • You have not subscribed to Caller ID service. Contact your service provider/telephone company to subscribe. • If your unit is connected to any additional telephone equipment such as a Caller ID box or cordless telephone line jack, disconnect the unit from the equipment and plug the unit directly into the wall jack. • If your unit is connected to a telephone line with DSL service, we recommend connecting a noise filter between the base unit and the telephone line jack. Contact your DSL provider for details. • The name display service may not be available in some areas. Contact your service provider/telephone company for details. • Other telephone equipment may be interfering with this unit. Disconnect the other equipment and try again. • The caller requested not to send caller information (page 23). • If a call is being transferred to you, the caller information is not displayed. • Generally, caller information is displayed from the 2nd ring.
The caller list/incoming phone numbers are not edited automatically.	<ul style="list-style-type: none"> • The Caller ID number auto edit feature is turned off. Turn it on and try again (page 28). • You need to call back the edited number to activate Caller ID number auto edit.
I cannot dial the phone number edited in the caller list.	<ul style="list-style-type: none"> • The phone number you dialed might have been edited incorrectly (for example, the long distance "1" or the area code is missing). Edit the phone number with another pattern (page 24).
Time on the unit is shifted.	<ul style="list-style-type: none"> • Incorrect time information from incoming Caller ID changes the time. Set "Time adjustment" off.

Useful Information

Problem	Cause/solution
The 2nd caller's information is not displayed during an outside call.	<ul style="list-style-type: none"> ● In order to use Caller ID, Call Waiting, or Call Waiting Caller ID (CWID), you must first contact your service provider/telephone company and subscribe to the desired service. After subscribing, you may need to contact your service provider/telephone company again to activate this specific service, even if you already subscribed to both Caller ID and Call Waiting with Caller ID services (CWID).

Answering system

Problem	Cause/solution
The unit does not record new messages.	<ul style="list-style-type: none"> ● The answering system is off. Turn it on (page 30). ● The message memory is full. Erase unnecessary messages (page 31). ● If you subscribe to the voice mail service, messages are recorded by your service provider/telephone company not your telephone. Change the unit's "Ring count" setting or consult your service provider/telephone company (page 35).
I cannot operate the answering system with the handset.	<ul style="list-style-type: none"> ● The base unit or another handset is being used. Wait for the other user to finish. ● A caller is leaving a message. Wait for the caller to finish. ● The handset is too far from the base unit. Move closer.
When I try to operate the answering system with the base unit, the ANSWER ON indicator on the base unit flashes for a few seconds and I cannot operate the answering system.	<ul style="list-style-type: none"> ● Another handset is being used. Wait for the other user to finish. ● A caller is leaving a message. Wait for the caller to finish.

Useful Information

Problem	Cause/solution
I cannot operate the answering system remotely.	<ul style="list-style-type: none"> ● You are entering the wrong remote access code. If you forget the remote access code, store a new remote access code again (page 34). ● Press each key firmly. ● The answering system is turned off. Turn it on (page 34). ● You are using a rotary/pulse telephone. Try again using a touch-tone phone.

Voice Mail

Problem	Cause/solution
"New Voice Mail" is not displayed on the handset even though I have new messages in my voice mail service.	<ul style="list-style-type: none"> ● Your service provider/telephone company needs to provide the signal for visual message waiting indicator. Consult your service provider/telephone company of your Voice Mail service. ● If you hear the "interrupted" dial tone, new messages are waiting. You can check if you have new messages by simply listening to the dial tone even if you cannot be provided the visual message waiting signal. ● To use the Voice Mail service provided by your service provider/telephone company rather than the unit's answering system, turn off the answering system (page 30).

Useful Information

FCC and other information

This equipment complies with Part 68 of the FCC rules and the requirements adopted by the ACTA. On the bottom of this equipment is a label that contains, among other information, a product identifier in the format US:ACJ-----.

If requested, this number must be provided to the telephone company.

- Registration No
.....(found on the bottom of the unit)
- Ringer Equivalence No.
(REN).....0.1B

A plug and jack used to connect this equipment to the premises wiring and telephone network must comply with the applicable FCC Part 68 rules and requirements adopted by the ACTA. A compliant telephone cord and modular plug is provided with the product. It is designed to be connected to a compatible modular jack that is also compliant.

The REN is used to determine the number of devices that may be connected to a telephone line. Excessive RENs on a telephone line may result in the devices not ringing in response to an incoming call. In most but not all areas, the sum of RENs should not exceed five (5.0). To be certain of the number of devices that may be connected to a line, as determined by the total RENs, contact the local telephone company. For products approved after July 23, 2001, the REN for the product is part of the product identifier that has the format US:AAAEQ##TXXXX. The digits represented by ## are the REN without a decimal point (e.g., 03 is a

REN of 0.3).

If this equipment causes harm to the telephone network, the telephone company will notify you in advance that temporary discontinuance of service may be required. But if advance notice isn't practical, the telephone company will notify the customer as soon as possible. Also, you will be advised of your right to file a complaint with the FCC if you believe it is necessary.

The telephone company may make changes in its facilities, equipment, operations or procedures that could affect the operation of the equipment. If this happens the telephone company will provide advance notice in order for you to make necessary modifications to maintain uninterrupted service.

If trouble is experienced with this equipment, for repair or warranty information, please contact a Factory Service Center or other Authorized Servicer. If the equipment is causing harm to the telephone network, the telephone company may request that you disconnect the equipment until the problem is resolved.

Connection to party line service is subject to state tariffs. Contact the state public utility commission, public service commission or corporation commission for information.

If your home has specially wired alarm equipment connected to the telephone line, ensure the installation of this equipment does not disable your alarm equipment. If you have questions

Useful Information

about what will disable alarm equipment, consult your telephone company or a qualified installer.

This equipment is hearing aid compatible as defined by the FCC in 47 CFR Section 68.316.

When you hold the phone to your ear, noise might be heard in your Hearing Aid. Some Hearing Aids are not adequately shielded from external RF (radio frequency) energy. If noise occurs, use an optional headset accessory or the speakerphone option (if applicable) when using this phone. Consult with your audiologist or Hearing Aid manufacturer about the availability of Hearing Aids which provide adequate shielding to RF energy commonly emitted by digital devices.

WHEN PROGRAMMING EMERGENCY NUMBERS AND/OR MAKING TEST CALLS TO EMERGENCY NUMBERS:

- 1) Remain on the line and briefly explain to the dispatcher the reason for the call.
- 2) Perform such activities in the off-peak hours, such as early morning or late evenings.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Privacy of communications may not be ensured when using this phone.

CAUTION:

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this device.

NOTE:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Some cordless telephones operate at frequencies that may cause interference to nearby TVs and VCRs. To minimize or prevent such interference, the base of the cordless telephone should not be placed near or on top of a TV or VCR. If

Useful Information

interference is experienced, move the cordless telephone further away from the TV or VCR. This will often reduce, or eliminate, interference.

FCC RF Exposure Warning:

- This product complies with FCC radiation exposure limits set forth for an uncontrolled environment.
- To comply with FCC RF exposure requirements, the base unit must be installed and operated 20 cm (8 inches) or more between the product and all person's body (excluding extremities of hands, wrist and feet).
- This product may not be collocated or operated in conjunction with any other antenna or transmitter.
- The handset may be carried and operated with only the specific provided belt-clip. Other non-tested belt-clips or similar body-worn accessories may not comply and must be avoided.

Notice

- FCC ID can be found inside the battery compartment or on the bottom of the units.

Notice

- This product is designed for use in the United States of America. Sale or use of this product in other countries may violate local laws.
- Cet appareil est conçu pour être utilisé aux États-Unis d'Amérique. La vente ou l'emploi de cet appareil dans certains autres pays peut constituer une infraction à la législation locale.
- Este producto está diseñado para usarse en los Estados Unidos de América. La venta o el empleo de este producto en ciertos países puede constituir violación de la legislación local.
- 本產品專為美國使用而設。若在其他國家銷售或使用，可能會違反當地法例。
- この製品は、日本国外での使用を目的として設計されており、日本国内での使用は法律違反となります。従って、当社では日本国内においては原則として修理などのサービスは致しかねます。

ENERGY STAR

As an ENERGY STAR® Participant, Panasonic has determined that this product meets the ENERGY STAR guidelines for energy efficiency. ENERGY STAR is a U.S. registered mark.



Useful Information

Specifications

- **Standard:**
DECT 6.0 (Digital Enhanced Cordless Telecommunications 6.0)
- **Number of channels:**
60 Duplex Channels
- **Frequency range:**
1.92 GHz to 1.93 GHz
- **Duplex procedure:**
TDMA (Time Division Multiple Access)
- **Channel spacing:**
1,728 kHz
- **Bit rate:**
1,152 kbit/s
- **Modulation:**
GFSK (Gaussian Frequency Shift Keying)
- **RF transmission power:**
Approx. 100 mW
- **Voice coding:**
ADPCM 32 kbit/s
- **Power source:**
120 V AC, 60 Hz
- **Power consumption:**

Base unit:
Standby: Approx. 1.8 W
Maximum: Approx. 5.0 W

Charger*1:
Standby: Approx. 0.7 W
Maximum: Approx. 3.5 W
- **Operating conditions:**
5 °C – 40 °C (41 °F – 104 °F),
20 % – 80 % relative air humidity (dry)
- **Dimensions:**

Base unit: Approx. 44 mm × 116 mm × 113 mm
(1 23/32 inches × 4 9/16 inches × 4 7/16 inches)

Handset: Approx. 143 mm × 47 mm × 32 mm

- (5 5/8 inches × 1 27/32 inches × 1 1/4 inches)

Charger*1: Approx. 46 mm × 77 mm × 87 mm
(1 13/16 inches × 3 1/32 inches × 3 7/16 inches)
- **Mass (weight):**

Base unit: Approx. 190 g (0.42 lb.)

Handset: Approx. 120 g (0.26 lb.)

Charger*1: Approx. 70 g (0.15 lb.)

*1 KX-TG8232

Note:

- Design and specifications are subject to change without notice.
- The illustrations in these instructions may vary slightly from the actual product.

Useful Information

Customer services

Customer Services Directory

Obtain Product Information and Operating Assistance; locate your nearest Dealer or Service Center; purchase Parts and Accessories; or make Customer Service and Literature requests by visiting our Web Site at:

<http://www.panasonic.com/help>

or, contact us via the web at:

<http://www.panasonic.com/contactus>

You may also contact us directly at: 1-800-211-PANA (1-800-211-7262), Monday - Friday 9 am to 9 pm; Saturday - Sunday 10 am to 7 pm, EST.

TTY users (hearing or speech impaired users) can call 1-877-833-8855.

Accessory Purchases

Purchase Parts, Accessories and Instruction Books online for all Panasonic Products by visiting our Web Site at:

<http://www.pasc.panasonic.com>

or, send your request by E-mail to:

npcparts@us.panasonic.com

You may also contact us directly at:

1-800-332-5368 (Phone) 1-800-237-9080 (Fax Only)

(Monday - Friday 9 am to 9 pm, EST.)

Panasonic Service and Technology Company

20421 84th Avenue South, Kent, WA 98032

(We Accept Visa, MasterCard, Discover Card, American Express, and Personal Checks.)

TTY users (hearing or speech impaired users) can call 1-866-605-1277.

Service in Puerto Rico

Panasonic Puerto Rico, Inc.

San Gabriel Industrial Park, Ave. 65 de Infantería, Km. 9.5,

Carolina, Puerto Rico 00985

Phone (787)750-4300, Fax (787)768-2910

Useful Information

Warranty

**PANASONIC CONSUMER
ELECTRONICS COMPANY, DIVISION
OF PANASONIC CORPORATION OF
NORTH AMERICA**
One Panasonic Way,
Secaucus, New Jersey 07094

PANASONIC PUERTO RICO, INC.
San Gabriel Industrial Park,
Ave. 65 de Infantería, Km. 9.5,
Carolina, Puerto Rico 00985

Panasonic Telephone Products Limited Warranty

Limited Warranty Coverage

If your product does not work properly because of a defect in materials or workmanship, Panasonic Consumer Electronics Company or Panasonic Puerto Rico, Inc. (collectively referred to as "the warrantor") will, for the length of the period indicated on the chart below, which starts with the date of original purchase ("Limited Warranty period"), at its option either (a) repair your product with new or refurbished parts, or (b) replace it with a new or a refurbished product. The decision to repair or replace will be made by the warrantor.

Parts	Labor
One (1) Year	One (1) Year

During the "Labor" Limited Warranty period there will be no charge for labor. During the "Parts" Limited Warranty period, there will be no charge for parts. You must mail-in your product prepaid during the Limited Warranty period. This Limited Warranty excludes both parts and labor for batteries, antennas, and cosmetic parts (cabinet). This Limited Warranty only applies to products purchased and serviced in the United States or Puerto Rico. This Limited Warranty is extended only to the original purchaser and only covers products purchased as new.

Mail-In Service

For assistance in the continental U.S.A. in obtaining repairs please ship the product prepaid to:

**Panasonic Service and Technology Company, Exchange Center,
4900 George McVay Drive, Suite B Door #12, McAllen, TX 78503**
panacare@us.panasonic.com

When shipping the unit carefully pack, include all accessories, and send it prepaid, adequately insured and preferably in the original carton. Include a letter detailing the complaint, a return address and provide a day time phone number where you can be reached. A valid registered receipt is required under the 1 year parts and labor Limited Warranty.

For Limited Warranty service for headsets if a headset is included with this product please call Panasonic at 1-800-332-5368.

For assistance in Puerto Rico call Panasonic Puerto Rico, Inc. (787)-750-4300 or fax (787)-768-2910.

Useful Information

IF REPAIR IS NEEDED DURING THE LIMITED WARRANTY PERIOD THE PURCHASER WILL BE REQUIRED TO FURNISH A SALES RECEIPT/PROOF OF PURCHASE INDICATING DATE OF PURCHASE, AMOUNT PAID AND PLACE OF PURCHASE. CUSTOMER WILL BE CHARGED FOR THE REPAIR OF ANY UNIT RECEIVED WITHOUT SUCH PROOF OF PURCHASE.

Limited Warranty Limits And Exclusions

This Limited Warranty ONLY COVERS failures due to defects in materials or workmanship, and DOES NOT COVER normal wear and tear or cosmetic damage. The Limited Warranty ALSO DOES NOT COVER damages which occurred in shipment, or failures which are caused by products not supplied by the warrantor, or failures which result from accidents, misuse, abuse, neglect, bug infestation, mishandling, misapplication, alteration, faulty installation, set-up adjustments, misadjustment of consumer controls, improper maintenance, power line surge, lightning damage, modification, introduction of sand, humidity or liquids, commercial use such as hotel, office, restaurant, or other business or rental use of the product, or service by anyone other than a Factory Service Center or other Authorized Servicer, or damage that is attributable to acts of God.

THERE ARE NO EXPRESS WARRANTIES EXCEPT AS LISTED UNDER "LIMITED WARRANTY COVERAGE". THE WARRANTOR IS NOT LIABLE FOR INCIDENTAL OR CONSEQUENTIAL DAMAGES RESULTING FROM THE USE OF THIS PRODUCT, OR ARISING OUT OF ANY BREACH OF THIS LIMITED WARRANTY. (As examples, this excludes damages for lost time, lost calls or messages, cost of having someone remove or re-install an installed unit if applicable, travel to and from the servicer. The items listed are not exclusive, but are for illustration only.) **ALL EXPRESS AND IMPLIED WARRANTIES, INCLUDING THE WARRANTY OF MERCHANTABILITY, ARE LIMITED TO THE PERIOD OF THE LIMITED WARRANTY.**

Some states do not allow the exclusion or limitation of incidental or consequential damages, or limitations on how long an implied warranty lasts, so the exclusions may not apply to you.

This Limited Warranty gives you specific legal rights and you may also have other rights which vary from state to state. If a problem with this product develops during or after the Limited Warranty period, you may contact your dealer or Service Center. If the problem is not handled to your satisfaction, then write to the warrantor's Consumer Affairs Department at the addresses listed for the warrantor.

PARTS AND SERVICE, WHICH ARE NOT COVERED BY THIS LIMITED WARRANTY, ARE YOUR RESPONSIBILITY.

Index

Index

- A** Alarm: 28
- Answering calls: 16
- Answering system
 - Erasing messages: 31, 32, 34
 - Listening to messages: 31, 32, 33
 - Remote operation: 33
 - Settings: 34
 - Turning on/off: 30, 32, 34
- Auto talk: 17
- B** Battery: 12, 13
- Belt clip: 40
- C** Call privacy: 17
- Call screening: 30, 35
- Call share: 17
- Call Waiting: 17
- Call Waiting Caller ID: 23
- Caller ID edit: 24
- Caller ID number auto edit: 24
- Caller ID service: 23
- Caller list: 24
- Chain dial: 21
- Conference calls: 37
- Connections: 11
- Customer support: 29
- D** Daily alarm: 29
- Date and time: 15
- Deregistration: 38
- Dialing mode: 15
- Display
 - Color: 26, 27
 - Contrast: 26, 27
 - Language: 14
 - Wallpaper: 26, 27
- E** Error messages: 41
- F** Flash: 17
- Flash time: 27
- G** Greeting message: 30
- Group
 - Display colors: 24
 - Ringer tones: 23
- H** Handset locator: 37
- Headset, optional: 4, 40
- I** Intercom: 37
- K** Key tone: 28
- M** Making calls: 16
- Memory capacity (message recording): 30
- Missed calls: 23
- Mute: 17
- O** One touch dial: 21
- P** Pause: 16
- Phonebook: 19
- Phonebook copy: 22
- Power failure: 11
- Pulse service: 17
- R** Recording time: 35
- Redial list: 16
- Registration: 38
- Remote code: 34
- Remote command: 33
- Remote operation: 33
- Ring count: 35
- Ringer off: 17, 27
- Ringer tone: 27
- Rotary service: 17
- S** Soft keys: 10
- SP-PHONE (Speakerphone): 16
- T** Time adjustment: 26
- Toll saver: 35
- Tone: 15, 17
- Transferring calls: 37
- Troubleshooting: 42
- TTY: 4, 52
- V** Voice guidance: 33
- Voice guidance language: 15
- Voice Mail: 35, 36
- Volume
 - Handset ringer: 27
 - Receiver: 10, 16
 - Speaker: 10, 16
- W** Warranty: 53

If you need assistance with setup or operation

- 1 Visit our website: <http://www.panasonic.com/help>
- 2 Contact us via the web at: <http://www.panasonic.com/contactus>
- 3 Call us at: 1-800-211-PANA (1-800-211-7262)
TTY users (hearing or speech impaired users) can call 1-877-833-8855.

When you ship the product

- Carefully pack your unit, preferably in the original carton.
- Attach a letter, detailing the symptom, to the outside of the carton.
- Send the unit to Panasonic Service and Technology Company, Exchange Center, prepaid and adequately insured.
- Do not send your unit to Panasonic Consumer Electronics Company listed below or to executive or regional sales offices. These locations do not repair consumer products.

We recommend keeping a record of the following information for future reference.

Serial No. _____ Date of purchase _____
(found on the bottom of the base unit)

Name and address of dealer _____

Attach your purchase receipt here.

**Panasonic Consumer Electronics Company,
Division of Panasonic Corporation of North America**
One Panasonic Way, Secaucus, New Jersey 07094

Panasonic Puerto Rico, Inc.
San Gabriel Industrial Park, Ave. 65 de Infantería, Km. 9.5,
Carolina, Puerto Rico 00985

Copyright:

This material is copyrighted by Panasonic Communications Co., Ltd., and may be reproduced for internal use only. All other reproduction, in whole or in part, is prohibited without the written consent of Panasonic Communications Co., Ltd.
© 2007 Panasonic Communications Co., Ltd. All Rights Reserved.



TG8231

PQQX16247ZB DC0707YK1077