

## **Owner's Manual**

Digital Wireless Stereo Headphones

Model No. RP-HD305B



**Bluetooth**°



Thank you for purchasing this product.

Please read these instructions carefully before using this product, and save this manual for future use.

Register online at <u>http://shop.panasonic.com/support</u> (U.S. customers only)

If you have any questions, visit: In the U.S.A.: http://shop.panasonic.com/support In Canada: www.panasonic.ca/english/support

PP

## IMPORTANT SAFETY INSTRUCTIONS

Read these operating instructions carefully before using the unit. Follow the safety instructions on the unit and the applicable safety instructions listed below. Keep these operating instructions handy for future reference.

- 1 Read these instructions.
- 2 Keep these instructions.
- 3 Heed all warnings.
- 4 Follow all instructions.
- 5 Do not use this apparatus near water.
- 6 Clean only with dry cloth.
- 7 Do not block any ventilation openings. Install in accordance with the manufacturer's instructions.
- 8 Do not install near any heat sources such as radiators, heat registers, stoves, or other apparatus (including amplifiers) that produce heat.
- 9 Do not defeat the safety purpose of the polarized or grounding-type plug. A polarized plug has two blades with one wider than the other. A grounding-type plug has two blades and a third grounding prong. The wide blade or the third prong are provided for your safety. If the provided plug does not fit into your outlet, consult an electrician for replacement of the obsolete outlet.
- 10 Protect the power cord from being walked on or pinched particularly at plugs, convenience receptacles, and the point where they exit from the apparatus.
- 11 Only use attachments/accessories specified by the manufacturer.
- 12 Use only with the cart, stand, tripod, bracket, or table specified by the manufacturer, or sold with the apparatus. When a cart is used, use caution when moving the cart/ apparatus combination to avoid injury from tip-over.



- 13 Unplug this apparatus during lightning storms or when unused for long periods of time.
- 14 Refer all servicing to qualified service personnel. Servicing is required when the apparatus has been damaged in any way, such as power-supply cord or plug is damaged, liquid has been spilled or objects have fallen into the apparatus, the apparatus has been exposed to rain or moisture, does not operate normally, or has been dropped.

## Safety precautions



A lithium ion battery that is recyclable powers the product you have purchased. Please call 1-800-8-BATTERY for information on how to recycle this battery.

This device complies with part 15 of FCC Rules and Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:

(1) this device may not cause harmful interference, and

(2) this device must accept any interference received, including interference that may cause undesired operation.

FCC ID: ACJ-RP-HD305B

Model: RP-HD305B

IC: 216A-RPHD305B

This transmitter must not be co-located or operated in conjunction with any other antenna or transmitter.

This equipment complies with FCC/ISED radiation exposure limits set forth for an uncontrolled environment and meets the FCC radio frequency (RF) Exposure Guidelines and RSS-102 of the ISED radio frequency (RF) Exposure rules as this equipment has very low levels of RF energy.

### THE FOLLOWING APPLIES ONLY IN THE U.S.A.

#### FCC Note:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Any unauthorized changes or modifications to this equipment would void the user's authority to operate this device.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Suppliers Declaration of Conformity

Trade Name: Panasonic

Model No.: RP-HD305B

Responsible Party: Panasonic Corporation of North America

Two Riverfront Plaza, Newark, NJ 07102-5490

Support Contact: http://shop.panasonic.com/support

#### THE FOLLOWING APPLIES ONLY IN CANADA.

CAN ICES-3(B)/NMB-3(B)

#### ∎ Unit

#### WARNING:

To reduce the risk of fire, electric shock or product damage,

- Do not expose this unit to rain, moisture, dripping or splashing.
- Do not place objects filled with liquids, such as vases, on this unit.
- Use the recommended accessories.
- Do not remove covers.
- Do not repair this unit by yourself. Refer servicing to qualified service personnel.
- Avoid using or placing this unit near sources of heat.
- Do not use while operating a motorized vehicle. It may create a traffic hazard and is illegal in many areas.
- Do not listen with this unit at high volume in places where you need to hear sounds from the surrounding environment for safety, such as at railroad crossings, and construction sites.
- Keep this unit away from something susceptible to the magnetism. Such devices as a clock may not operate correctly.

#### Allergies

- Discontinue use if you experience discomfort with the ear pads or any other parts that directly contact your skin.
- Continued use may cause rashes or other allergic reactions.

Use only the supplied USB charging cord when connecting to a computer.



Intertek

3123480

CONFORMS TO UL STD. 62368-1 S CERTIFIED TO CSA STD. C22.2 NO. 62368-1 CONFORME À LA NORME CAN/CSA C22.2 NO. 62368-1



## About Bluetooth®

## Panasonic bears no responsibility for data and/or information that is compromised during a wireless transmission.

#### Frequency band used

This unit uses the 2.4 GHz frequency band.

#### Certification of this unit

- This unit conforms to frequency restrictions and has received certification based on frequency laws. Thus, a wireless permit is not necessary.
- The actions below are punishable by law in some countries:
  - Taking apart/modifying this unit.
  - -Removing specification indications.

#### Restrictions of use

- Wireless transmission and/or usage with all Bluetooth® equipped devices is not guaranteed.
- All devices must conform to standards set by Bluetooth SIG, Inc.
- Depending on the specifications and settings of a device, it can fail to connect or some operations can be different.
- This unit supports Bluetooth<sup>®</sup> security features. But depending on the operating environment and/or settings, this security may not be sufficient. Transmit data wirelessly to this unit with caution.
- This unit cannot transmit data to a Bluetooth<sup>®</sup> device.

#### ■Range of use

Use this unit at a maximum range of 10 m (33 ft.).

The range can decrease depending on the environment, obstacles or interference.

#### ■ Interference from other devices

- This unit may not function properly and troubles such as noise and sound jumps may arise due to radio wave interference if this unit is located too close to other Bluetooth<sup>®</sup> devices or the devices that use the 2.4 GHz band.
- This unit may not function properly if radio waves from a nearby broadcasting station, etc. is too strong.

#### Intended usage

- This unit is for normal, general use only.
- Do not use this system near an equipment or in an environment that is sensitive to radio frequency interference (example: airports, hospitals, laboratories, etc).

## Table of contents

IMPORTANT SAFETY INSTRUCTIONS	2
Safety precautions	3
About Bluetooth <sup>®</sup>	5

#### Before use

Accessories	. 7
Maintenance	. 7
Part names	. 8

#### Preparation

Charging	. 9
Furning the power on/off	. 9
Connecting a Bluetooth <sup>®</sup> device	10
Pairing (Registration) this unit with the Bluetooth <sup>®</sup> device for connection	
Connecting a paired Bluetooth <sup>®</sup> device	11

#### Operation

Listening to music 12	2
Remote controlling	2
Selecting the sound mode	3
14 Making a phone call	
Useful functions	5
Activating voice functions	5
Guidance messages	5
Battery level notification	5
Auto power off	5
Using the detachable cord (supplied)	3
• Resetting the unit	3

#### Other

Restoring to the factory settings 1	
Copyright, etc 1	17
Troubleshooting1	18
Sound and audio volume1	18
Bluetooth® device connection1	18
Phone Calls	18
• General1	19
Power supply and charging1	19
Guidance messages	19
Specifications	
To remove the battery when disposing of this unit 2	21

#### Expressions used in this document

- Pages to be referred to are indicated as "→ ○○".
- The product illustrations may differ from the actual product.

### Accessories

Please check and identify the supplied accessories.

Only for U.S.A.:

To order accessories, refer to "Limited Warranty (ONLY FOR U.S.A.)" on "Basic Owner's Manual". Only for Canada:

To order accessories, contact the dealer from whom you have made your purchase.

- 1 x USB charging cord
- 1 x Detachable cord

### Maintenance


Clean this unit with a dry and soft cloth.

• Do not use solvents including benzine, thinner, alcohol, kitchen detergent, a chemical wiper, etc. This might cause the exterior case to be deformed or the coating to come off.

Keeping the battery performance.

• During the long period of disuse, full charge this unit once every 6 months to keep the battery performance.

### Part names



- 1 Audio input terminal
- 2 [SOUND] button
- 3 [+] button
- 4 [►/II/ ͡ゝ] button
- 5 [-] button
- 6 Charging terminal (DC IN)
  - Connect the USB charging cord (supplied) to this terminal when charging. (→ 9)
- \*1 Examples of lighting/blinking patterns

- 7 Power/pairing LED<sup>\*1</sup>
- 8 [Ů/I (₿)] button<sup>\*2</sup>
- 9 Microphone
- 10 Ear pads
- 11 Raised dot indicating the left side

Lighting (red):	Charging is in progress
Lighting alternately in blue and red:	Bluetooth <sup>®</sup> pairing (registration) standby
Blinking slowly (blue) <sup>*3</sup> :	Bluetooth <sup>®</sup> connection standby
Blinking twice about every 2 seconds (blue) <sup>*3</sup> :	A Bluetooth <sup>®</sup> pairing (registration) has been established or a call is in progress
Blinking (blue) <sup>*3</sup> :	A call is being received

\*2 也/I: Standby/ON


\*3 The battery is low when it is blinking in red. (> 15, "Battery level notification")

## Charging

The rechargeable battery (installed in the unit) is not charged initially. Charge the battery before using the unit.

## Connect this unit to a computer using the USB charging cord.

- A: Power/pairing LED
- B: USB charging cord (supplied)
  - Check the direction of the terminals and plug in/out straight holding onto the plug. (It may result in malfunction by the deforming of the terminal if it is plugged in obliquely or in wrong direction.)
- G: Computer
  - Turn on the computer in advance.
- The power/pairing LED lights in red when charging is in progress. When charging is completed, the power/ pairing LED will go out.
- It takes approx. 5 hours to charge the battery from empty to full.



#### Note

- Charge in a room temperature between 10 °C and 35 °C (50 °F and 95 °F). Outside of this temperature range, charging may stop and the power/pairing LED may go out.
- It is not possible to turn the power on or connect to Bluetooth<sup>®</sup> devices during charging.
- Do not use any other USB charging cords except the supplied one. Doing so may cause malfunction.
- Charging may not be performed or may stop if the computer is in or switched to standby or sleep mode.

## Turning the power on/off

# In the power-off state, press and hold [也/I (酚)] of this unit for approx. 3 seconds until the power/pairing LED (blue) blinks.

• A beep will sound, and the power/pairing LED (blue) will blink slowly.

#### To turn the power off

Press and hold [0/I (S)] for approximately 3 seconds. An English guidance message will be heard, and the power will be turned off.

• It is possible to switch the audio guidance between English and French.

( $\rightarrow$  15, "Guidance messages")

Right (R) side	
Power/pairing LED [Ů/l (🌒)]	

- If the unit is not connected to a Bluetooth<sup>®</sup> device, an English guidance message will be heard and turn off the unit automatically approximately 5 minutes after you have stopped using it. (→ 15, "Auto power off")
- It is possible to switch the audio guidance between English and French. (> 15, "Guidance messages")

## Connecting a Bluetooth<sup>®</sup> device

#### Preparation

- Place the Bluetooth<sup>®</sup> device within approx. 1 m (3.3 ft.) from the unit.
- Check the device operation using its operation instructions as required.

#### Pairing (Registration) this unit with the Bluetooth $^{ extsf{B}}$ device for connection

1 In the power-off state, press and hold [也/I (段)] of this unit until the power/pairing LED blinks.

When pairing a device for the first time:

approx. 3 seconds


When pairing a second or subsequent devices:

approx. 5 seconds

- This unit will start to search for a Bluetooth<sup>®</sup> device to connect to, and the power/pairing LED will light alternately in blue and red.
- 2 Turn on the power of the Bluetooth<sup>®</sup> device, and enable the Bluetooth<sup>®</sup> function.

#### 3 Select "RP-HD305B" from the Bluetooth<sup>®</sup> device's menu.

- A MAC address (an alphanumeric character string that is displayed by and unique to the device) may be displayed before "RP-HD305B" is displayed.
- If prompted for a passkey, input the passkey "0000 (four zeros)" of this unit.



## 4 Check the connection with the Bluetooth<sup>®</sup> device on the unit.

• The power/pairing LED will light alternately in blue and red until the connection with the device is completed. When the power/pairing LED (blue) blinks twice every approx. 2 seconds, pairing (registration) is completed. (Connection established)

- If connection to a device is not established within approximately 5 minutes, the unit will be turned off. Perform pairing again.
- You can pair up to 8 Bluetooth<sup>®</sup> devices with this unit. If a 9th device is paired, the device with the oldest connection will be replaced. To use it, perform pairing again.

#### Connecting a paired Bluetooth<sup>®</sup> device

#### 1 Turn on this unit.

- Press and hold [U/I ())] of this unit for approx. 3 seconds until the power/pairing LED (blue) blinks.
- A beep will sound, and the power/pairing LED (blue) will blink slowly.
- 2 Perform steps 2 and 3 of "Pairing (Registration) this unit with the Bluetooth<sup>®</sup> device for connection". (→ 10)
  - When the power/pairing LED (blue) blinks twice every approx. 2 seconds, pairing (registration) is completed. (Connection established)

- This unit remembers the device lastly connected. Connection may be automatically established after step 1 (see above).
- If connection to a device is not established within approximately 5 minutes, the unit will be turned off. Turn on the unit again.

## Listening to music

If the Bluetooth<sup>®</sup> compatible device supports the "A2DP" and "AVRCP" Bluetooth<sup>®</sup> profiles, music can be played back with remote control operations on the unit.

- A2DP (Advanced Audio Distribution Profile): Transmits audio to the unit.
- AVRCP (Audio/Video Remote Control Profile): Allows remote control of the device using the unit.

#### 1 Connect the Bluetooth<sup>®</sup> device and the unit. ( $\rightarrow$ 10, "Connecting a Bluetooth<sup>®</sup> device")

#### 2 Select and play the music on the Bluetooth<sup>®</sup> device.

- The unit's headphones will output the music or the audio of the video being played back.
- Operating time:

The maximum playback time is approximately 24 hours. (It may become shorter depending on the usage conditions.)

#### Attention

- The unit might leak sound depending on the volume level.
- When the volume is increased to near maximum level, music may sound distorted. Decrease the volume until the distortion is cleared.

#### **Remote controlling**

You can control the Bluetooth<sup>®</sup> device using the unit.

• Depending on the Bluetooth<sup>®</sup> device or the app, even if you press buttons on the unit, some functions may not respond or may operate differently from the descriptions below.

#### (Operation example)



Function	Operation
Play / Pause	Press [▶/Ⅲ/ ͡ゝ].
Increase the volume	Press [+].
Decrease the volume	Press [-].
Forward to the start of next track	Press [▶/Ⅲ/ î) twice quickly.
Return to the start of current track	Press [▶/Ⅲ/ î͡\$] three times quickly.
Fast forward	Press [►/II/ ͡ゝ] twice quickly; hold the second press.
Fast rewind	Press [►/II/ ͡\$] three times quickly; hold the third press.

#### Note

• The volume can be adjusted in 31 levels (16 levels during calls). When the maximum or minimum volume is reached, a beep will sound.

#### Selecting the sound mode

This changes the sound quality of the music or video being played back.

#### Press the [SOUND] button on this unit.

· Each press of this button changes the sound quality.

- Bass Enhancer : Produces a more dynamic sound effect with enhanced bass.
- Clear Voice : Produces a sound effect which makes human voices, such as vocals and dialogues, clear to listen to.
- OFF : Turns off sound effects.

Bass Enhancer	$\rightarrow$	Clear Voice	→ 0	FF
Ť				1

- The setting immediately before the power is turned off is stored.
- You will be notified by audio guidance when the mode is switched.
- It is possible to switch the audio guidance between English and French. (> 15, "Guidance messages")
- This may not be effective depending on the music or video being played back.

## Making a phone call

With Bluetooth<sup>®</sup> enabled phones (cell phones or smartphones) that support the "HSP" or "HFP" Bluetooth<sup>®</sup> profile, you can use the unit for phone calls.

• HSP (Headset Profile):

This profile can be used to receive monaural sounds and establish two-way communication using the microphone on the unit.

• HFP (Hands-Free Profile):

In addition to the HSP functions, this profile has the incoming and outgoing calls function.

(This unit does not have a function that allows you to make phone calls independently of a Bluetooth<sup>®</sup> enabled phone.)

#### 1 Connect the Bluetooth<sup>®</sup> device and the unit. ( $\rightarrow$ 10, "Connecting a Bluetooth<sup>®</sup> device")


#### 2 Press [►/II/ ] on the unit and answer the incoming call.

- During an incoming call, ringtone will sound from the unit and the power/ pairing LED will blink.
- (HFP only) To reject the incoming call, press [>/II/ ] twice quickly.

#### 3 Start talking.

- The power/pairing LED will repeatedly blink 2 times during a call.
- The volume can be adjusted during a phone call. For setting instructions, see page 12.
- 4 Press [►/II/ ] to end the phone call.
  - A beep will sound.

- There may be instances when hands free setting needs to be done on the Bluetooth<sup>®</sup> enabled phone.
- Depending on the Bluetooth<sup>®</sup> enabled phone, you may hear incoming and outgoing call ringtones of the phone from the unit.
- (HFP only) It may be difficult to hear phone conversations when the unit is used in locations with loud ambient noise or in outdoor or other locations exposed to powerful winds. In that case, change the calling location or switch the calling device to the Bluetooth<sup>®</sup> enabled phone to continue the call. (Press [►/II/ ) on the unit twice quickly to switch.)
- You can have the Bluetooth<sup>®</sup> enabled phone make phone calls by using the microphone of the unit and an app of the Bluetooth<sup>®</sup> enabled phone. (→ 15, "Activating voice functions")



## **Useful functions**

#### Activating voice functions

You can use a button on this unit to activate Siri or other voice functions on your smartphone or similar device.

#### 1 Connect the Bluetooth<sup>®</sup> device and the unit. (→ 10, "Connecting a Bluetooth<sup>®</sup> device")

#### 2 Press and hold [>/II/ ] on this unit until the voice function is activated.

#### Note

• For details about voice function commands, refer to the operating instructions for the Bluetooth® device.

• The voice function may not work depending on the smartphone, etc., specifications and the app version.

#### Guidance messages

The unit is equipped with an a function that provides an audio notification when you turn on/off the unit, connect a Bluetooth<sup>®</sup> device or change a setting, for example.

- This unit has English and French messages for the audio guidance.
- The audio guidance function cannot be disabled.
- The audio guidance volume cannot be adjusted.

#### Switching the audio guidance language

#### Press and hold [-] and $[\bigcirc/I (\bigcirc)]$ for at least 5 seconds.

#### **Battery level notification**

- When the unit is turned off, an English guidance message will be heard indicating the battery level.
- When the battery level starts to run low, the blinking power/pairing LED will turn from blue to red, and as it drops further, you will be notified by one beep every 1 minute.\* When the battery runs out, an English guidance message will be heard and the power will turn off.
- \* If you press [U/I ()] twice quickly, an English guidance message will be heard and you can check the battery level.
- It is possible to switch the audio guidance between English and French. (→ above)

#### Auto power off

If the unit is not connected to a Bluetooth<sup>®</sup> device, an English guidance message will be heard and turn off the unit automatically approximately 5 minutes after you have stopped using it.

It is possible to switch the audio guidance between English and French. (→ above)


#### Using the detachable cord (supplied)

While the power is turned off or the battery has no remaining charge, this unit can be used as normal headphones by connecting the detachable cord (supplied).

- Before connecting the detachable cord (supplied), lower the volume on the connected device.
- If you connect the detachable cord (supplied) when connected via  $\mathsf{Bluetooth}^{\textcircled{B}}$ , the power will turn off.
- Noise may occur due to dirt on the plug. Clean the plug with a soft dry cloth if this occurs.
- Do not use any other detachable cords except the supplied one.

#### Resetting the unit

This unit can be reset when all operations are rejected. To reset the unit, connect the unit to a computer using the USB charging cord. All the previous operations will be canceled. (The pairing device information will not be deleted.)



## Restoring to the factory settings

When you want to delete all pairing device information, etc., you can restore the unit to the factory settings (original settings upon purchase). Charge the battery before restoring the unit.

- 1 While the power is turned off, press and hold [U/I ()] for at least 5 seconds until the power/pairing LED lights alternately in blue and red.
- 2 While the power/pairing LED is lighting alternately in blue and red, press [+] and [-] at the same time for at least 5 seconds.

• The default settings will be restored after the power/pairing LED (blue) blinks fast and the unit turns off.

#### Attention

• When pairing a device again, delete the registering information (Device: "RP-HD305B") from the Bluetooth<sup>®</sup> device's menu, and register this unit with the Bluetooth<sup>®</sup> device again. (→ 10)

## Copyright, etc.

The Bluetooth<sup>®</sup> word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Panasonic Corporation is under license.

Other trademarks and trade names are those of their respective owners.

Siri is a trademark of Apple Inc.

Qualcomm aptX is a product of Qualcomm Technologies, Inc. and/or its subsidiaries. Qualcomm is a trademark of Qualcomm Incorporated, registered in the United States and other countries. aptX is a trademark of Qualcomm Technologies International, Ltd., registered in the United States and other countries.

Other system names and product names appearing in this document are in general the registered trademarks or trademarks of the respective developer companies. Note that the <sup>™</sup> mark and <sup>®</sup> mark do not appear in this document.

## Troubleshooting

Before requesting service, make the following checks. If you are in doubt about some of the check points, or if the remedies indicated in the chart do not solve the problem, refer to "Customer Services Directory" on "Basic Owner's Manual" if you reside in the U.S.A., or refer to "CONTACT INFORMATION" on "Basic Owner's Manual" if you reside in the U.S.A.

#### Sound and audio volume

#### No sound.

- Make sure that the unit and the Bluetooth<sup>®</sup> device are connected correctly. ( $\rightarrow$  10)
- Check if music is playing on the Bluetooth<sup>®</sup> device.
- Make sure that the unit is turned on and the volume is not set too low.
- Pair and connect the Bluetooth<sup>®</sup> device and the unit again. ( $\rightarrow$  10)
- Check if the Bluetooth<sup>®</sup> compatible device supports "A2DP" profile. For details on profiles, see "Listening to music"
  (→ 12). Also refer to the operating manual for the Bluetooth<sup>®</sup> compatible device.
- If there is more than one active Bluetooth<sup>®</sup> device around this unit, it may be connected to the wrong one, so check that it is connected to the correct one.

#### Cannot adjust the volume.

• The control buttons on this unit are disabled when the detachable cord (supplied) is being used.

#### Low volume.

- Increase the volume of the unit. (→ 12)
- ${\mbox{ }}$  Increase the volume on the  ${\mbox{ Bluetooth}}^{\mbox{ } \mbox{ }}$  device.

#### Sound from the device is cut off. / Too much noise. / Sound quality is bad.

- Sound may be disrupted if signals are blocked. Do not fully cover this unit with the palm of your hand, etc.
- The device may be out of the 10 m (33 ft.) communication range. Move the device closer to this unit.
- Remove any obstacle between this unit and the device.
- Switch off any wireless LAN device when not in use.

#### Bluetooth<sup>®</sup> device connection

#### The device cannot be connected.

- You can pair up to 8 Bluetooth<sup>®</sup> devices with this unit. If a 9th device is paired, the device with the oldest connection will be replaced.
- Delete the pairing information for this unit from the Bluetooth<sup>®</sup> device, then pair them again. ( $\rightarrow$  10)

#### Phone Calls

#### You cannot hear the other person.

- Make sure that the unit and the Bluetooth<sup>®</sup> enabled phone are turned on.
- Check if the unit and the Bluetooth<sup>®</sup> enabled phone are connected. (→ 10)
- Check the audio settings of the Bluetooth<sup>®</sup> enabled phone. Switch the calling device to the unit if it is set to the Bluetooth<sup>®</sup> enabled phone. (→ 10)
- If the volume of the other person's voice is too low, increase the volume of both the unit and the Bluetooth<sup>®</sup> enabled phone.

#### Cannot make a phone call.

Check if the Bluetooth<sup>®</sup> compatible device supports "HSP" or "HFP" profile. For details on profiles, see "Listening to music" (→ 12) and "Making a phone call" (→ 14). Also refer to the operating manual for the Bluetooth<sup>®</sup> enabled phone.

#### General

#### The unit does not respond.

- This unit can be reset when all operations are rejected. To reset the unit, connect the unit to a computer using the USB charging cord. (→ 16)
- The power cannot be turned on when the detachable cord (supplied) is connected.

#### Power supply and charging

## Cannot charge the unit. / The power/pairing LED does not light during charging. / Charging takes longer.

- Is the USB charging cord connected firmly to the USB terminal of the computer? (→ 9)
- Make sure to charge in a room temperature between 10 °C and 35 °C (50 °F and 95 °F).
- Make sure the computer is turned on and is not on standby or sleep mode.
- Is the USB port you are currently using working properly? If your computer has other USB ports, unplug the connector from its current port and plug it into one of the other ports.
- · If the measures mentioned above are not applicable, unplug the USB charging cord and plug it in again.
- It takes approx. 5 hours to charge the battery from empty to full.
- If the charge time and operating time become shortened, the battery may have run down. (Number of charging times of the installed battery: Approximately 300)
- The power/pairing LED lights in red when charging is in progress. When charging is completed, the power/pairing LED will go out.

#### The power does not turn on. / The power turns off.

- Is the unit being charged? The power cannot be turned ON during charging. (→ 9)
- The battery is low when the power/pairing LED is blinking in red. Charge the unit.
- Is auto power off active? (→ 15)
- The power cannot be turned on when the detachable cord (supplied) is connected.

#### **Guidance messages**

#### The audio guidance language has changed.

The audio guidance language can be switched. (→ 15)

## **Specifications**

#### General

Power supply	DC 5 V, 300 mA (Internal battery: 3.7 V (Li-polymer))
Operating time <sup>*1</sup>	Approx. 24 hours (SBC)
Charging time <sup>*2</sup> (25 °C (77 °F))	Approx. 5 hours
Charging temperature range	10 °C to 35 °C (50 °F to 95 °F)
Operating temperature range	0 °C to 40 °C (32 °F to 104 °F)
Operating humidity range	35 %RH to 80 %RH (no condensation)
Mass (Weight)	Approx. 218 g (7.7 oz) (without cord)

\*1 It may be shorter depending on the operating conditions.

\*2 The time required to charge the battery from empty to full.

#### ■ Bluetooth<sup>®</sup> section

Bluetooth <sup>®</sup> system specification	Ver. 5.0
Wireless equipment classification	Class 2 (2.5 mW)
Maximum RF Power	4 dBm
Frequency band	2402 MHz to 2480 MHz
Supported profiles	A2DP, AVRCP, HSP, HFP
Supported codec	SBC, AAC, Qualcomm <sup>®</sup> aptX <sup>TM</sup> , Qualcomm <sup>®</sup> aptX <sup>TM</sup> Low Latency
Operating distance	Up to 10 m (33 ft.)

#### Headphone section

Impedance	34 $\Omega$ (Power off, with cord)
Frequency response	4 Hz to 40000 Hz (with cord)

#### Speaker section

Driver units	40 mm (1 - 9/16 inch)
Max input	1000 mW (IEC)

#### Terminal section

DC IN	DC 5 V, 500 mA
-------	----------------

#### Microphone section

Туре М	Лопо
--------	------

#### Accessory section

USB charging cord	Approx. 0.5 m (1.6 ft.)
Detachable cord	Approx. 2.0 m (6.6 ft.)

• Specifications are subject to change without notice.

## To remove the battery when disposing of this unit

The following instructions are not intended for repairing purposes but for the disposal of this unit. This unit is not restorable once disassembled.

• When disposing of this unit, take out the battery installed in this unit and recycle it.

• Disassemble after the battery runs out.

·Keep disassembled parts out of reach of children.

#### Regarding the handling of used batteries


- Insulate the terminals with adhesive tape or similar material.
- Do not disassemble.

#### Batteries

- Do not heat or expose to flame.
- Do not leave the battery(ies) in a car exposed to direct sunlight for a long period of time with doors and windows closed.

2

- Battery mishandling can cause electrolyte leakage which can damage items the leaked fluid comes into contact with. If electrolyte leaks from the battery, consult your dealer. Wash thoroughly with water if electrolyte comes in contact with any part of your body.
- When disposing of the batteries, please contact your local authorities or dealer and ask for the correct method of disposal.







- 1 Insert a flat-head screwdriver into the groove on the outward-facing side of the left headphone (()).
- 2 Use the flat-head screwdriver to pry up ().
- 3 Remove the battery, and cut off the wires one by one with scissors.

Panasonic Corporation of North America Two Riverfront Plaza, Newark, NJ 07102-5490 http://shop.panasonic.com

Panasonic Canada Inc. 5770 Ambler Drive, Mississauga, Ontario L4W 2T3 www.panasonic.com

(En)